



OMNITRONIC LH-060 PRO Passive dual DI box

2-channel DI box/splitter, passive

- Converts 2 separate unbalanced line inputs (e.g. instruments) into 2 balanced XLR outputs, for connecting a mixer
- 2 high-impedance signal inputs via combo connectors (XLR/6.3 mm jack)
- 2 XLR/jack input connectors (unbal.), 2 XLR outputs (bal.)
- Split mode



No. 10355060

Technical specifications:

Frequency range:	15 Hz - 30 kHz
Input impedance:	50 kohms
Output impedance:	600 ohms
Maximum output level:	6 dBu
Dynamic range:	>95 dB
Input connectors:	2 x combo XLR/6.3 mm jack
Output connectors:	2 x XLR, bal.
Dimensions:	150 x 130 x 60 mm
Weight:	0.5 kg



OMNITRONIC LH-061 PRO Passive dual DI box

2-channel DI box/splitter, passive

- Converts 2 separate unbalanced line inputs (e.g. CD player) into 2 balanced XLR outputs, for connecting a mixer
- 2 high-impedance signal inputs via two 6.3 mm jacks
- 2 low-impedance XLR outputs
- 2 feed-through outputs (6.3 mm jack)



No. 10355061

Technical specifications:

Frequency range:	15 Hz - 30 kHz
Input impedance:	50 kohms
Output impedance:	600 ohms
Maximum output level:	6 dBu
Dynamic range:	>95 dB
Input connectors:	2 x 6.3 mm jack
Output connectors:	2 x XLR
	2 x 6.3 mm jack (parallel out)
Dimensions:	115 x 133 x 54 mm
Weight:	0.6 kg



OMNITRONIC LH-065 Active DI box

1-channel DI box, active

- Converts an unbalanced line input (e.g. instruments) into a balanced XLR output for connecting a mixer
- XLR/6.3 mm jack input (unbal.), feed-through output (6.3 mm jack, unbal.)
- XLR output (bal.)
- Switchable input attenuation: 0 dB, -20 dB, -40 dB



No. 10355065

Technical specifications:

Power supply:	9 V battery
Current consumption:	approx. 65 mA
Battery life:	6 - 8 hours
Frequency range:	10 Hz - 30 kHz
Input impedance:	470 kohms
Output impedance:	600 ohms
Input connectors:	XLR and 6.3 mm jack, unbal.
Output connectors:	XLR, bal.
	6.3 mm jack, unbal. (parallel out)
THD:	0.5 %
Dimensions:	150 x 130 x 60 mm
Weight:	0.5 kg



OMNITRONIC LH-068 DI box phantom powered

1-channel DI box, phantom powered, active

- Converts an unbalanced line input (e.g. instruments) into a balanced XLR output for connecting a mixer
- 6.3 mm jack input (unbal.)
- Feed-through output (6.3 mm jack, unbal.)
- XLR output (bal.)
- Operates on +48 V phantom power



No. 10355068

Technical specifications:

Power supply:	9-48 V DC phantom power
Frequency range:	1 Hz - 50 kHz
S/N ratio:	100 dB
Input connector:	6.3 mm jack, unbal.
Input level:	-10 dB to +40 dB
Output connectors:	XLR, bal.
	6.3 mm jack, unbal. (parallel out)
Output level:	-10 dB to +2 dB
Dimensions:	95 x 80 x 40 mm
Weight:	0.5 kg



OMNITRONIC LH-071 Active dual DI box

Dual DI box/splitter

- Active 2-channel DI box with split mode
- Converts 2 separate unbalanced line inputs (e.g. instruments) into 2 balanced XLR outputs, for connecting a mixer
- 2 high-impedance signal inputs via combo connectors (XLR/6.3 mm jack)
- 2 low-impedance XLR outputs
- Input sensitivity switchable: +20 dB, 0 dB, -30 dB



No. 10355071

Technical specifications:

Power supply:	9 V battery
Current consumption:	approx. 65 mA
Battery life:	6 - 8 hours
Frequency range:	10 Hz - 30 kHz
Input impedance:	470 kohms
Output impedance:	600 ohms
Maximum output level:	6 dBu
Input connectors:	2 x combo XLR/6.3 mm jack
Output connectors:	2 x XLR, bal.
THD:	0.5 %
Dimensions:	150 x 130 x 60 mm
Weight:	0.5 kg