

## OMNITRONIC MCX-4250 100V adaptor 1U

Transformateur audio à 4 canaux

Réf. : 80709580

GTIN: 4026397306118



## L'article n'est plus disponible.

### Description:

Adapt yourself!

The keyword is upgrading. Cars are upgraded with partical filters, computers get a software update and TVs a digital receiver. In the audio field can be upgraded as well. If you want to use the 100 voltage technic for example, but don't have the suitable amplifier which transforms the low impedance to 100 voltage, here comes a affordable solution: The OMNITRONIC MCX-4250. This adapter adjusts to your old amplifier so you can keep on using it and wont have to replace it. Therefore you can easily distribute the signal with your amplifier to a ELA system while define 4 zones separately. And with only one height unit, the MCX-4250 is very compact and wont take much space. Upgrading the easy way, isn't it?

### Logistique

EAN / GTIN: 4026397306118

Poids: 20,00 kg

Longueur: 0.58 m

Largeur: 0.56 m

Hauteur: 0.11 m

### Caractéristiques:

- Output transformer for power amplifiers or speakers without built-in 70 V or 100 V audio transformer
- 4 x 250 W
- Use your existing amplifier for distributing the sound signal in a PA system
- Converts low-impedance signals into 70 V or 100 V signals
- Connections via terminal blocks
- Signal indicators
- Rugged steel chassis
- Rack installation, 1 U

### Données techniques:

Puissance de sortie: Max. 400 W

Plage de fréquence:	50 - 16000 Hz
Dimension:	Largeur : 48,3 cm Profondeur : 49 cm Hauteur : 4,45 cm
Poids:	18,50 kg
Output power:	4 x 250 W
Output type:	70 V or 100 V
Distortion factor:	<1 %
Connectors:	4 terminal blocks
Indicators:	signal
Construction:	steel chassis
Dimensions:	482 x 490 x 48 mm Rack installation with 1 U
Minimum mounting depth:	510 mm