



OMNITRONIC PM-408 DJ mixer

Professional 3-channel DJ mixer

- 3-channel DJ battle mixer
- Inputs: 4 x line, 2 x phono/line, 1 x DJ microphone
- 3-band equalizer with kill switch
- XLR master out



No. 10006818

Technical specifications:

Power supply:	230 V AC, 50 Hz ~
Power consumption:	5 W
Inputs:	
DJ MIC:	6.3 mm jack
Minimum input voltage:	1.5 mV RMS/ 1 kohm
LINE 1-6:	stereo RCA
Minimum input voltage:	150 mV RMS/ 270 kohm
PHONO 1-2:	stereo RCA
Minimum input voltage:	3 mV RMS/ 470 kohm
Outputs:	
MASTER:	stereo RCA, stereo XLR (3-pin)
BOOTH:	stereo RCA
Max. output level:	+22 dBu
Output voltage:	9 V RMS
REC:	stereo RCA
Output voltage:	225 mV RMS/ 5 kohm
Headphones:	6.3 mm stereo jack/ 16 ohm
Tone control:	
3 x High:	-12 dB to +12 dB/ 1 kHz
3 x Middle:	-12 dB to +12 dB/ 1 kHz
3 x Low:	12 dB to +12 dB/ 1 kHz
S/N ratio:	>80 dB
Frequency range:	20-25000 Hz
Distortion:	0.05% (line/phono)
Dimensions (WxHxD):	262 x 255 x 110 mm
Weight:	2.8 kg



OMNITRONIC PM-404 DJ mixer

Professional 2-channel DJ mixer

- 2-channel DJ battle mixer
- Inputs: 2 x line/phono, 1 x DJ microphone
- 3-band equalizer with kill switch



No. 10006817

Technical specifications:

Power supply:	230 V AC, 50 Hz ~, via supplied power unit
Power consumption:	5 W
Inputs:	
DJ MIC:	6.3 mm jack
Minimum input voltage:	1.5 mV RMS/ 1 kohms
LINE 1-2:	stereo RCA
Minimum input voltage:	150 mV RMS/ 270 kohms
PHONO 1-2:	stereo RCA
Minimum input voltage:	3 mV RMS/ 470 kohms
Outputs:	
MASTER:	stereo RCA
Max. output level:	+22 dBu
Output voltage:	9 V RMS
REC:	stereo RCA
Output voltage:	225 mV RMS/ 5 kohms
Headphones:	6.3 mm stereo jack/ 16 ohms
Tone control:	
2 x High:	-26 dB to +12 dB/ 12 KHz
2 x Middle:	±15 dB/ 2.5 KHz
2 x Low:	-26 dB to +12 dB/ 80 Hz
S/N ratio:	>80 dB
Frequency range:	20-20000 Hz
Distortion:	<0.02% (line/phono)
Dimensions (WxHxD):	262 x 255 x 84 mm
Weight:	2.8 kg