



USB

**OMNITRONIC PM-444USB 4-channel DJ mixer**

Professional 4-channel DJ mixer with USB interface

- Club mixer with integrated USB audio interface (bi-directional In/Out)
- Inputs: 1 x USB, 5 x line, 2 x phono
- 1 DJ microphone channel
- Balanced XLR outputs



No. 10006823

**Technical specifications:**

Power supply:	100-240 V AC, 50/60 Hz ~
Power consumption:	25 W
USB port:	2.0, type B
Inputs:	
DJ MIC (front):	combined 3-pin XLR/6.3 mm jack (bal.)
Impedance:	1 kohms
Minimum input voltage:	10 mV RMS
LINE 1-4:	stereo RCA
Impedance:	1 kohms
Minimum input voltage:	300 mV RMS
PHONO 1,2:	stereo RCA
Impedance:	1 kohms
Minimum input voltage:	3 mV RMS
Outputs:	
MASTER:	stereo RCA, XLR L/R (bal.)
Output voltage:	3 V RMS
REC:	stereo RCA
Output voltage:	7 V RMS
Headphones:	6.3 mm stereo jack (>16 ohms)
Tone control (DJ MIC):	
1 x High:	-30 dB to +12 dB/ 10 kHz, ±1 dB
1 x Low:	-30 dB to +12 dB/ 100 Hz, ±1 dB
Tone control (ch 1-4):	
1 x High:	-30 dB to +12 dB/ 40 kHz, ±1 dB
1 x Low:	-30 dB to +12 dB/ 40 kHz, ±1 dB
S/N ratio:	60 dB
Frequency range:	20-20,000 Hz
Dimensions (WxHxD):	483 x 177 x 101 mm (19", 4 U)
Weight:	2.9 kg



**OMNITRONIC PM-222 2-channel DJ mixer**

2-channel DJ mixer

- 4 line/2 phono inputs
- Gain control and 2-band equalizer
- Microphone and headphones inputs



No. 10006819

**Technical specifications:**

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	30 W
Inputs:	
DJ MIC:	6.3 mm jack
Minimum input voltage:	3 mV RMS/ 47 kohms
LINE:	stereo RCA
Minimum input voltage:	150 mV RMS/ 47 kohms
PHONO:	stereo RCA
Minimum input voltage:	3 mV RMS/ 47 kohms
Outputs:	
MASTER:	stereo RCA
Max. output level:	+19 dBu
Output voltage:	7 V RMS
REC:	stereo RCA
Output voltage:	2.4 V RMS
Headphones:	6.3 mm stereo jack (min. 32 ohms)
Tone control:	
2 x High:	-24 dB to +15 dB/ 12 kHz
2 x Low:	-24 dB to +15 dB/ 100 Hz
S/N ratio:	>70 dB
Frequency range:	20-20,000 Hz
Distortion:	<0.025%
Dimensions (LxWxH):	260 x 190 x 137 mm
Weight:	2 kg