



**OMNITRONIC LS Powered live mixer**

Powered live mixer

- Output power 2 x 150/200/300 W/4 ohms
- Low noise Mic/Line mixer with 6/8/12 channels
- 2/4/8 mono inputs with XLR sockets
- Insert or Direct Out for every mono channel

- No. 10060050.....LS-622A
- No. 10060100.....LS-822A
- No. 10060200.....LS-1222A



**Technical specifications:**

Device:	LS-622A	LS-822A	LS-1222A
Power supply:	115/230 V AC, 50/60 Hz ~	115/230 V AC, 50/60 Hz ~	115/230 V AC, 50/60 Hz ~
Power consumption:	500 W	800 W	800 W
Inputs:			
Mono	2 XLR or balanced 6.3 mm jacks	4 XLR or balanced 6.3 mm jacks	8 XLR or balanced 6.3 mm jacks
Inserts	2 6.3 mm jacks	4 6.3 mm jacks	8 6.3 mm jacks
2 stereo	balanced 6.3 mm jacks	balanced 6.3 mm jacks	balanced 6.3 mm jacks
1 Aux-Return	balanced 6.3 mm jacks	balanced 6.3 mm jack	balanced 6.3 mm jack
Tape In	RCA	RCA	RCA
Outputs:			
1 Main Mix Out	XLR or balanced 6.3 mm jacks	XLR or balanced 6.3 mm jacks	XLR or balanced 6.3 mm jacks
1 Headphone	balanced 6.3 mm jack	balanced 6.3 mm jack	balanced 6.3 mm jack
1 Aux-Send	balanced 6.3 mm jack	balanced 6.3 mm jack	balanced 6.3 mm jack
Direct Out	2 6.3 mm jacks	4 6.3 mm jacks	8 6.3 mm jacks
Tape Out	RCA	RCA	RCA
Frequency range:			
Microphone:			
Mono:	10 Hz - 60 kHz, ±3 dB	10 Hz - 60 kHz, ±3 dB	10 Hz - 60 kHz, ±3 dB
Stereo:	10 Hz - 55 kHz, ±3 dB	10 Hz - 55 kHz, ±3 dB	10 Hz - 55 kHz, ±3 dB
Distortion:	0.01 %	0.01 %	0.01 %
S/N-ratio:	112 dB	112 dB	112 dB
Tone control/channel:			
Treble:	±15 dB at 12 KHz	±15 dB at 12 KHz	±15 dB at 12 KHz
Middle:	±15 dB at 2.5 KHz	±15 dB at 2.5 KHz	±15 dB at 2.5 KHz
Bass:	±15 dB at 80 Hz	±15 dB at 80 Hz	±15 dB at 80 Hz
Power output sine:			
Stereo 4 ohms	2 x 150 W	2 x 200 W	2 x 300 W
Dimensions (WxDxH):	330 x 390 x 125 mm	390 x 390 x 150 mm	550 x 390 x 125 mm
Weight:	9.5 kg	10 kg	13 kg