

19" RJ45



OMNITRONIC MCS-1250 MK2 6-zone PA amplifier

6-zone audio amplifier with matrix assignment,
2 x 50 W pro zone

- 6-channel audio amplifier multi-zone PA applications
- Updated version with touch pad wall controller
- 12 x 50 W/4 ohms
- Efficient Class D technology
- 6 stereo inputs expandable to 18 stereo zones with further units
- Matrix input assignment: input sources are freely assignable to each channel
- 6 pre-amp outputs to connect external power amplifiers
- Optical input

No. 10452480

Technical specifications:

Power supply:	230 V AC, 50 Hz ~
Power consumption (max.):	1250 W
Output power sine:	
Stereo 4 ohms:	2 x 50 W per zone
Stereo 8 ohms:	2 x 25 W per zone
8 ohm bridged:	6 x 100 W
Frequency range:	20-20000 Hz
Distortion:	0.1 % (1 kHz)
S/N ratio:	85 dB
Input sensitivity:	250 mV
Input impedance:	>47 kohm
Speaker connectors:	Terminal block
Home automation interface:	RS-232
Muting:	12 V DC, via 3.5 mm mono jack
Trigger output:	12 V DC, via 3.5 mm mono jack
IR emitter connectors:	12 V DC, via 3.5 mm mono jack
LED indicators (per channel):	standby/on, peak
Protection circuits:	short-circuit, overheat, overload
Dimensions:	482 x 420 x 102 mm (19", 2 U)
Weight:	13.6 kg



RJ45

OMNITRONIC MCS-1250 MK2 Keypad

MCS-1250 MK2 touch pad wall controller

- Touch-sensitive surface
- LCD with blue backlight for monitoring the zone settings
- Allows selecting and adjusting each zone individually: audio source, volume, treble, bass, mute, on/off
- Wiring to amp via hub and network cable (RJ-45)
- Surface mounting, with IR receiver

No. 10452483



RJ45

OMNITRONIC MCS-1250 MK2 Hub

MCS-1250 MK2 hub

- Hub for connecting up to 6 wall controllers to the amplifier MCS-1250 MK2

No. 10452484



OMNITRONIC MCS-1250 MK2 remote control

MCS-1250 MK2 IR remote control

- IR remote control for the amplifier MCS-1250 MK2 and the corresponding wall controllers

No. 10452485



OMNITRONIC MCS-1250 MK2 IR emitter

IR remote emitter for MCS-1250 MK2

- Operate your audio/video equipment in other rooms with your existing remote control
- The MCS-1250 MK2 wall controller picks up the signal from your remote control and the IR emitter sends the signal to the A/V component
- Supports all standard A/V components (HDD recorder, set-top box, satellite decoder and stereo) with an infrared sensor

No. 10452486