

Innovative colour-changer

- DMX-controlled operation or stand alone operation with Master/Slave-function
- 48 preprogrammed scenes in Program Run for stand alone operation
- Number of scenes in Program Run can be changed individually
- The scenes in Program Run can be modified via the Control Board or via an external controller and loaded into the memory
- 8 built-in programs can be called up via DMX-controller
- Sound-controlled via built-in microphone
- Control-Board with 4-digit display and foil-keyboard for adjusting the DMX-starting address, Program, Reset, lamp on/off
- For bright HPL 575 W lamp
- Colour-wheel 1 with 5 different, dichroic colour-filtres and white
- Colour-wheel 2 with 4 different, dichroic colour-filtres, blackout and white
- DMX-control via every standard DMX-controller
- 4 DMX-control-channels required
- Suitable FUTURELIGHT controllers: EX-6 controller, CP-256/32 Controller

**Technical specifications:**

| | |
|-----------------------|-------------------------------|
| Power supply: | 230 V AC, 50 Hz ~ |
| Power consumption: | 585 W |
| DMX-control-channels: | 4 |
| DMX-512-connection: | 3-pin XLR |
| Sound-control: | via built-in microphone |
| Colour-wheel 1: | 5 colours and white |
| Colour-wheel 2: | 4 colours, blackout and white |
| Dimensions (LxWxH): | 325 x 435 x 350 mm |
| Weight: | 12 kg |

Accessory:

| | |
|--|--------------|
| GE HPL575 240V/575W 300h 3200K | No. 88315000 |
| GE HPL575X 240V/575W 1500h 3050K Longl | No. 88315700 |
| Barndoors for PCC-250/PCC-500 | No. 51840955 |
| FUTURELIGHT EX-6/32 controller | No. 51834046 |
| FUTURELIGHT EX-8/32 controller | No. 51834047 |
| FUTURELIGHT CP-240 controller | No. 51834265 |
| FUTURELIGHT CP-256 controller 16bit | No. 51834285 |
| FUTURELIGHT CP-256/32 controller 16bit | No. 51834286 |
| FUTURELIGHT CP-528 controller 16bit | No. 51834315 |
| Wizard-512 USB DMX-Software + Interface | No. 51860102 |
| Wizard-1024 USB DMX-Software + Interface | No. 51860110 |
| FUTURELIGHT DES-3 DMX-terminator 3-pin | No. 51834001 |