

Extremely powerful colour-changer

- DMX-controlled operation or stand alone operation with Master/Slave-function
- 48 preprogrammed scenes in Program Run for stand alone operation
- Number of scenes in Program Run can be changed individually
- The scenes in Program Run can be modified via the Control Board or via an external controller and loaded into the memory
- 8 built-in programs can be called up via DMX-controller
- Sound-controlled via built-in microphone
- Control-Board with 4-digit display and foil-keyboard for adjusting the DMX-starting address, Program, Reset, lamp on/off
- For bright 1200 W lamp
- Colour-wheel 1 with 5 different, dichroic colour-filtres and white
- Colour-wheel 2 with 4 different, dichroic colour-filtres, blackout and white
- DMX-control via every standard DMX-controller
- 4 DMX-control-channels required
- Suitable FUTURELIGHT controllers: EX-6 controller, CP-256/32 Controller

**Technical specifications:**

Power supply: 230 V AC, 50 Hz ~
 Power consumption: 1250 W
 DMX-control-channels: 4
 DMX-512-connection: 3-pin XLR
 Sound-control: via built-in microphone
 Colour-wheel 1: 5 colours and white
 Colour-wheel 2: 4 colours, blackout and white
 Dimensions (LxWxH): 470 x 410 x 450 mm
 Weight: 18 kg

Accessory:

GE CP93 240V/1200W G-22 200h 3200K	No. 88463000
OMNILUX 240V/1200W G-22 200h 3200K	No. 88463005
OSRAM 64756 230V/1200W G-22 200h	No. 88463010
Barndoors for PCC-1200	No. 51840980
FUTURELIGHT EX-6/32 controller	No. 51834046
FUTURELIGHT EX-8/32 controller	No. 51834047
FUTURELIGHT CP-240 controller	No. 51834265
FUTURELIGHT CP-256 controller 16bit	No. 51834285
FUTURELIGHT CP-256/32 controller 16bit	No. 51834286
FUTURELIGHT CP-528 controller 16bit	No. 51834315
Wizard-512 USB DMX-Software + Interface	No. 51860102
Wizard-1024 USB DMX-Software + Interface	No. 51860110
FUTURELIGHT DES-3 DMX-terminator 3-pin	No. 51834001