

OMNITRONIC PM-444USB 4-Channel DJ mixer

4-channel DJ mixer with USB interface

Art. No.: 10006823

GTIN: 4026397453423



The article is no longer in our assortment.

Features:

- Built-in USB audio interface allows recordings and playback of digital audio files with a computer (PC and Mac)
- Full duplex USB port allows simultaneous recording and playback
- 4 channels with gain control, 2-band equalizer, cue button and channel fader
- 1 DJ microphone channel with talkover selector and 2-band equalizer
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Replaceable crossfader for crossfading between input channels with assignment switches
- Master channel with level control and stereo LED level meter
- Outputs: master (stereo XLR/RCA), record (stereo RCA), headphones (6.3 mm jack)
- The device can be connected via USB to the PC
- (19") 48.3 cm rack installation 4 U

Package contents

- 1 x mixer, 1 x user manual, 1 x power cord, 1 x USB cable

Logistic

EAN / GTIN: 4026397453423

Weight: 3,50 kg

Length: 0.56 m

Width: 0.25 m

Height: 0.16 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	25,00 W
Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)

Frequency range:	20 - 20000 Hz
S/N ratio:	>60 dB
Impedance:	Input: microphone 1 kOhm Input: line 1 kOhm Input: phono 1 kOhm
Gain:	Input: variable
Control elements:	Crossfader selector switch, crossfader, source selector, power switch
Status LED:	Power, CUE, master level meter, chanal level meter
Connections:	Input: microphone via 1 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version) Input: line via 5 x stereo RCA Input: phono via 2 x stereo RCA Output: master via 2 x 3-pin XLR Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: rec. via 1 x USB B (F) mounting version Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input channel: 2 x stereo with line-phono switch via RCA, channel control via fader, 2-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control Input channel: 1 x stereo with line-line switch via RCA, channel control via fader, 2-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control, CUE switch Input channel: 1 x stereo with line-USB switch via RCA or USB, channel control via fader, 2-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control Microphon chanal: 1 x mono via Combination socket (XLR/jack), channel control via rotary dial, 2-band tone control EQ -30dB to12dB at 70Hz/13kHz, cue mix function Master output: 1 x stereo via XLR or RCA, channel control via rotary dial Headphones output: stereo via jack, channel control via rotary dial
USB port:	USB 2.0, type B
PC connect:	Via USB
Housing design:	(19") 48.3 cm rack installation 4 U
Dimensions:	Width: 48,3 cm Depth: 17,8 cm Height: 8,9 cm
Weight:	2,90 kg