

OMNITRONIC PM-444Pi 4-channel DJ Mixer with Player & USB Interface

4-channel DJ mixer with Bluetooth, MP3 player and USB interface

Art. No.: 10006825

GTIN: 4026397704815



Features:

- 4 input channels with gain control, LED level meter, 3-band equalizer, cue button and channel fader
- 1 DJ microphone channel with level control, 2-band equalizer, on/off and talkover switch
- Built-in USB audio interface allows playback of digital audio files from a computer (PC and Mac)
- Prefader listening to input channels and the master output via adjustable headphones output, with cue mix/split function
- Crossfader with assignment switches
- Master channel with level and balance control
- 10-digit stereo LED level meter
- Adjustable monitor output
- 7 line and 2 phono inputs via RCA jacks
- Balanced XLR and RCA outputs
- Additional recording output
- (19") 48.3 cm rack installation 4 U
- Control via Bluetooth
- LCD display
- The device can be connected via USB to the PC
- For application areas such as: Clubs/dancing school; installation; mobile djs / entertainer; restaurants, bars and hotels

Logistic

EAN / GTIN: 4026397704815

Weight: 3,95 kg

Length: 0.49 m

Width: 0.22 m

Height: 0.14 m

Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption: Max. 10 W

Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>60 dB
Impedance:	Input: microphone 1 kOhm Input: line 1 kOhm Input: phono 1 kOhm
Gain:	Input: variable
Control:	Bluetooth
Bluetooth:	Version: 4.2 + EDR Profiles: A2DP, AVRCP
Bluetooth device name:	PM-444Pi
Housing color:	Black
Display type:	LCD display
Control elements:	Crossfader selector switch, crossfader, source selector, power switch
Status LED:	Power, CUE, master level meter, channel level meter
Connections:	Input: microphone via 1 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version) Input: line via 5 x stereo RCA Input: phono via 2 x stereo RCA Output: master via 2 x 3-pin XLR Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input channel: 2 x stereo with line-phono switch via RCA, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control, CUE switch, crossfader selector switch, source selector Input channel: 1 x stereo with line-line switch via RCA, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control, CUE switch Input channel: 1 x stereo with line-USB switch via RCA or USB, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control Microphone channel: 1 x mono via Combination socket (XLR/jack), channel control via rotary dial, 2-band tone control EQ -30dB to12dB at 70Hz/13kHz Master output: 1 x stereo via XLR or RCA, channel control via rotary dial Headphones output: stereo via jack, channel control via rotary dial
Music format:	MP3, WAV; WAV
USB port:	USB 2.0, type B Type A
PC connect:	Via USB
Housing design:	(19") 48.3 cm rack installation 4 U

Dimensions:	Width: 48.3 cm
	Depth: 17.8 cm
	Height: 8.9 cm
<hr/>	
Weight:	3.50 kg
<hr/>	
Available storage media:	USB devices max. 32GB (FAT 32)
<hr/>	

Scope of delivery:

- 1 x user manual
- 1 x power cord
- 1 x mixer
- 1 x RCA cable
- 1 x USB cable