

## OMNITRONIC PM-311 DJ mixer

3-channel DJ mixer

Art. No.: 10006876

GTIN: 4026397467154



### Features:

- 3 input channels, switchable 2 x phono/line and 1 x aux/line
- Front aux input for portable music players (e.g. iPod)
- All input channels with gain control, 3-band equalizer and cue button
- DJ microphone input with talkover selector, level and 3-band equalizer
- Pre-fader listening (CUE) to the input channels and the master output via adjustable headphones output, with cue mix control
- Crossfader for crossfading between the phono/line channels
- 5-digit stereo LED level meter, switchable between master and PFL signal
- Additional recording output
- Operation via supplied power unit

### Logistic

EAN / GTIN: 4026397467154

Weight: 2,20 kg

Length: 0.34 m

Width: 0.24 m

Height: 0.12 m

### Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 4.00 W

Frequency range: 20 - 20000 Hz

Dimensions:  
Width: 26 cm  
Depth: 17.2 cm  
Height: 7.8 cm

Weight: 1.90 kg

via supplied power unit

**Inputs:**

|                |                     |
|----------------|---------------------|
| Line/phono:    | 2 x stereo RCA      |
| Line:          | stereo RCA          |
| Aux:           | 3.5 mm stereo jack  |
| DJ microphone: | 6.3 mm jack, unbal. |

**Outputs:**

|                    |                                   |
|--------------------|-----------------------------------|
| Master:            | stereo RCA                        |
| Record:            | stereo RCA                        |
| Headphones output: | 6.3 mm stereo jack (min. 32 ohms) |
| S/N ratio:         | >75 dB                            |
| Distortion:        | <0.07 %                           |

**Scope of delivery:**