

OMNITRONIC EM-550B MK2 Entertainment Mixer

Multifunctional 5+2-channel installation mixer, black

Art. No.: 10007103

GTIN: 4026397714333



List price: 415.31 €

incl. 19% VAT.

Features:

- 5 input channels with recessed gain controls on the rear panel, signal LED and smooth channel faders
- Prefader listening to input channels and the master output via adjustable headphones output, with cue mix/split function
- 2 adjustable master outputs with 3-way equalizer and 10-digit stereo LED level meter
- (19") 48.3 cm rack installation 2 U
- For application areas such as: Installation; restaurants, bars and hotels; clubs/dancing school

Package contents

- 1 x mixer, 1 x user manual, 1 x power cord, 1 x RCA cable

Logistic

EAN / GTIN: 4026397714333

Weight: 3,46 kg

Length: 0.50 m

Width: 0.14 m

Height: 0.18 m

Technical specifications:

| | |
|--------------------|---|
| Power supply: | 230 V AC, 50 Hz |
| Power consumption: | 9 W |
| Protection class: | Protection class II |
| Power connection: | Power supply cord with Euro plug (provided) |
| Frequency range: | 20 - 20000 Hz |
| S/N ratio: | >65 dB line/phono |
| THD: | Line/phono <0,02 % at 1 kHz |
| Gain: | Microphone 52 dB Line 19 dB |

| | |
|-------------------|--|
| | Phono 54 dB |
| Housing color: | Black |
| Control elements: | Power switch, regular talkover, source selector |
| Status LED: | Signal, master level meter, peak, chanal source; CUE, talkover, ON AIR, routing |
| Connections: | <p>Input: microphone via 2 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version)</p> <p>Input: line/phono via 2 x stereo RCA</p> <p>Input: line via 9 x stereo RCA</p> <p>Output: master via 2 x 3-pin XLR</p> <p>Output: master via 2 x stereo RCA</p> <p>Output: headphones via 1 x 6.3-mm-jack (bal.)</p> <p>Output: booth via stereo RCA</p> <p>Output: rec. via 2 x stereo RCA</p> |
| Channels: | <p>Input channel: 2 x stereo with line-line/phono switch via RCA, channel control via fader, , gain control, source selector, CUE switch</p> <p>Input channel: 3 x stereo with line-line switch via RCA, channel control via fader, , gain control, source selector, CUE switch</p> <p>Microphon chanal: 2 x mono via Combination socket (XLR/jack), channel control via rotary dial, 3-band tone control EQ, ON AIR switch, talkover switch</p> <p>Master output: 2 x stereo via XLR or RCA, channel control via rotary dial, 3-band tone control EQ</p> <p>Rec. output: 2 x stereo via RCA, NO MIC switch</p> <p>Headphones output: 1 x stereo via jack, channel control via rotary dial, cue mix split function</p> <p>Booth output: 1 x mono + stereo via RCA, channel control via rotary dial</p> <p>Input channel: 1 x stereo via RCA, channel control via rotary dial</p> |
| Housing design: | (19") 48.3 cm rack installation 2 U |
| Dimensions: | <p>Width: 48,3 cm</p> <p>Depth: 14,8 cm</p> <p>Height: 8,9 cm</p> |
| Weight: | 3,10 kg |