

OMNITRONIC RRM-502 5-channel rotary mixer

5-channel rotary mixer for DJs

Art. No.: 10355925

GTIN: 4026397566017



The article is no longer in our assortment.

Features:

- Classic rotary mixer with 5 input channels for DJs
- Vintage ALPS potentiometers (Blue Velvet RK27)
- High-grade components ensure long life and excellent sound quality
- Gain control, cue button and source selector per channel
- 10 line inputs, 3 of which switchable phono/line
- DJ microphone channel with separate level control and 2-band EQ
- Prefader listening to input channels and the master output via adjustable headphones output, with cue mix/split function
- Master, booth and balance control
- Record output, switchable pre/post
- FX send/return for external FX unit
- Rack installation, 2 U
- (19") 48.3 cm rack installation 2 U

Logistic

EAN / GTIN: 4026397566017

Weight: 5,50 kg

Length: 0.53 m

Width: 0.17 m

Height: 0.28 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	15 W
Protection class:	Protection class I
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Device fuse:	5 x 20 mm, T 0,5 A fuse replaceable

Frequency range:	20 - 20000 Hz microphone 20 - 20000 Hz line 40 - 18000 Hz phono
S/N ratio:	>78 dB phono >80,5 dB microphone >89 dB line
THD:	Line <0,02 % at 1 kHz Phono <0,1 % at 1 kHz
Gain:	Input: line 20 dB Input: phono 75 dB Input: microphone 44 dB
Control elements:	Cue mix split function, crossfader
Status LED:	Power, CUE
Connections:	Input: line via 7 x stereo RCA Input: line/phono via 3 x stereo RCA Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version Insert: master via 2 x stereo RCA Output: master via 2 x 3-pin XLR Output: master via 1 x stereo RCA Output: booth via 2 x 3-pin XLR Output: booth via 1 x stereo RCA Output: rec. via 1 x stereo RCA Link: line via 1 x stereo RCA
Channels:	Input channel: 3 x stereo with line-line/phono switch via RCA, channel control via rotary dial, 2-band tone control EQ, gain control, CUE switch Input channel: 2 x stereo with line-line switch via RCA, channel control via rotary dial, CUE switch Microphon channel: 1 x mono via jack, channel control via rotary dial, balancecontrol Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol Booth output: 1 x stereo via XLR or RCA, channel control via rotary dial, cue mix split function Headphones output: 1 x stereo via jack, channel control via rotary dial, pre-post switch Rec. output: 1 x stereo via RCA
Max. level:	Output: +22 dBu
Housing design:	(19") 48.3 cm rack installation 2 U
Dimensions:	Width: 48,3 cm Depth: 20 cm Height: 8,9 cm
Weight:	4,73 kg