

OMNITRONIC B-3600 Amplifier

High performance amplifier 2 x 1800 W/4 ohms

Art. No.: 10451830

GTIN: 4026397351392



The article is no longer in our assortment.

Description:

Impressive peak power!

Like all technical fields audio technology has to be up-to-date. As in professional use the expectations for quality and power are high, a further development is all the more important. With the B series, OMNITRONIC presents its new top league of professional PA amplifiers. Equipped with powerful and high-grade power supplies, these power packs can generate up to 3,600 watts. Therefore, they perfectly feed power-hungry subwoofers and big tops. A particularly useful feature is the LCD status display: You can see all important operating conditions such as the temperature. Allowing you to keep track even with large setups.

Features:

- Class H construction: 2-step power output
- Enormous power with highest brilliance
- 2 gain controls on the front panel
- All operation modes controllable via LCD display
- Signal inputs via XLR-mounting sockets
- Signal outputs for daisy-chaining via XLR connector
- Speaker connection via lockable Speaker plugs
- Many protection circuits for optimized equipment protection
- High-Cut and Low-Cut with a crossover frequency of 120 Hz, switch positions SUB, FULLRANGE, SAT
- Very rugged housing with recessed screws
- Rack installation with 3 units

Logistic

EAN / GTIN: 4026397351392

Weight: 40,15 kg

Length: 0.65 m

Width: 0.59 m

Height: 0.21 m

Bulky product

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	1440,00 W
Output power:	Max. 3600 W
Dimensions:	Width: 48,3 cm Depth: 48,9 cm Height: 8,9 cm
Weight:	35,76 kg
Power output sine:	
Stereo 4 ohms	2 x 1800 W
Stereo 8 ohms	2 x 1000 W
8 ohms bridged	1 x 3600 W
Frequency range:	20-20000 Hz, ± 0.5 dB
Damping factor:	>700
Distortion factor:	0.5 %
Signal-to-noise ratio:	>95 dB
Channel separation (at 1 kHz):	>60 dB
Input impedance:	20 kohms (balanced)
Input connectors:	2 x XLR mounting socket
Output connectors:	2 x Speaker (stereo)
Control elements:	Power switch, input attenuators (one per channel), Mode switch - Stereo/Parallel/Bridged, Ground Lift
LED indicators:	
Global:	Stereo, Parallel, Bridge
Per channel:	Signal, Clip/Limit, Protect
Protection circuits:	Short-circuit, overvoltage, DC, thermal, softstart
Construction:	Steel chassis, aluminum front panel