

OMNITRONIC MCS-1250 12-channel amplifier

6-channel audio amplifier with matrix assignment 12 x 50 W/4 ohms

Art. No.: 10452491

GTIN: 4026397286427



The article is no longer in our assortment.

Description:

Amplifier of unlimited possibilities!

Perhaps the MCS-1250's possibilities are not unlimited, but they are definitely numerous. Let's take a look at a locality that consists of several rooms for instance. Now, each room should have its own music, but due to space problems, only a compact and centrally located amplifier unit can be installed. Not an issue. The MCS-1250 offers the possibility to operate six zones simultaneously. Each zone is equipped with a controller that is able to separate the zones and to adjust them individually. So the volume, the basses and the heights can be set as required. Really a nice one!

Features:

- 12 x 50 W/4 ohms
- Ideal for multi-zone applications
- 6 stereo inputs expandable to 18 stereo zones with further units
- Matrix input assignment: input sources are freely assignable to each channel
- Volume, Treble, Bass adjustment with controller MCS-1250R for each output individually
- Incl. IR remote control
- Incl. 6 controllers MCS-1250R
- Signal inputs via stereo RCA sockets
- Signal outputs via terminal blocks
- Bridged switch for bridging
- LED indicators on the front panel
- Rack installation

Package contents

- 1 x remote control

Logistic

EAN / GTIN: 4026397286427

Weight: 13,55 kg

Length: 0.56 m

Width: 0.53 m

Height: 0.23 m

Technical specifications:

Power supply:	115/230 V AC, 50/60 Hz
Power consumption:	1250,00 W
Output power:	Max. 600 W
Frequency range:	20 - 20000 Hz
Dimensions:	Width: 48,3 cm Depth: 42 cm Height: 8,9 cm
Weight:	11,25 kg
Remote control	
Battery:	2 x button cell 3.0 V CR2025 lithium manganese built-in
Output power sine:	
Stereo 4 ohms:	12 x 50 W
Stereo 8 ohms:	12 x 25 W
8 ohms bridged:	6 x 100 W
Distortion:	0.01 % (1 kHz)
S/N ratio:	85 dB
Input sensitivity:	250 mV
Input impedance:	>47 kohms
Zone input connectors:	6 x stereo RCA
Link:	RS-232
Zone output connectors:	Terminal blocks
Controller connector:	RJ45
LED indicators (per channel):	Signal
Dimensions:	482 x 420 x 102 mm