

## RELACART UR-260D 2-channel UHF System 823-832 + 863-865 MHz

System with DSP for microphone modeling and PC software, 823-832 + 863-865 MHz

Art. No.: 13055212

GTIN: 4026397525786



**List price: 617.61 €**

incl. 19% VAT.

### Description:

The UR-260D is a dual-channel true diversity UHF system with a host of innovative features. In addition to automatic frequency scanning for interference-free transmission, one also finds an intelligent feedback suppression system. With MagicEQ, various sound characteristics of world-known microphone capsules can be emulated or created yourself. The presets can be changed from a computer via software - even during live operation.

### Logistic

EAN / GTIN: 4026397525786

Weight: 3,80 kg

Length: 0.59 m

Width: 0.43 m

Height: 0.09 m

### Features:

System with DSP for microphone modeling and PC software, 823-832 + 863-865 MHz

- 1 x receiver, 2 x antenna, 1 x external mains adapter, 2 x microphone, 1 x jack cable, 1 x mounting bracket, 1 x bag, 1 x user manual, 1 x declaration of conformity

### RELACART UR-260D 2-channel UHF Receiver 823-832 + 863-865 MHz

Diversity wireless receiver with DSP for microphone modeling and PC software

- 2-channel multifrequency wireless receiver with 24-bit processor for high-end audio quality
- Integrated MagicEQ enables amazing microphone modeling of hand-held microphones
- Choose from 7 presets based on popular microphone models (e835, beta58, e935, D5, SM57, N/D767a, SM58) and 3 user-definable presets
- Integrated Feedback Killer effectively eliminates feedback, providing maximum gain and increased clarity on every microphone
- DSP programming and management via Ethernet port and intuitively operated PC software
- High-quality antenna diversity reception
- 10 groups with 90 fixed frequencies within 11 MHz switching bandwidth

- Pilot frequency squelch technology delete wireless RF interference
  - Automatic frequency scan (AFS) finds interference-free channels
  - Easy and error-free synchronization between receiver and transmitter via infrared signal
  - Multiple units can be linked with network cables
  - Lock function for prevents undesired changes to settings
  - 2 detachable BNC antennas allow for use with the R-14D antenna divider
  - Rugged metal housing
  - (19") 48.3 cm rack installation possible 1 U
  - Digital signal processor 96kHz, 24 bit
  - Operating range up to 80m
  - UHF 863 - 865 MHz License-free and approved in Europe
  - UHF 823 - 832 MHz License-free and approved in large parts of Europe
  - Up to 9 transmitters can be operated in parallel without interference
  - Multicolor LCD display
  - The device can be connected via RJ-45 (F) mounting version to the PC in connection with RELACART Magic EQ software
  - Desktop console housing
- Package contents**
- 1 x receiver, 2 x antenna, 1 x external mains adapter, 1 x jack cable, 2 x mounting bracket, 6 x screw, 1 x user manual, 1 x declaration of conformity

#### RELACART UH-222D Microphone 823-832 + 863-865 MHz

Hand-held microphone with PLL multifrequency transmitter

- Dynamic hand-held microphone with UHF pilot tone technology (PLL)
  - Ergonomic aluminum alloy housing, applicable for touring
  - 10 groups with 90 fixed frequencies within 11 MHz switching bandwidth
  - Easy and error-free synchronization between receiver and transmitter via infrared signal
  - RF output power Hi/Low adjustable
  - Gain level Hi/Mid/Low adjustable
  - Capsule M-022
  - Directly compatible with Shure's SM58 capsule
  - Polar pattern: Super cardioid
  - Operating range up to 80m
  - UHF 863 - 865 MHz License-free and approved in Europe
  - UHF 823 - 832 MHz License-free and approved in large parts of Europe
  - OLED display
  - Charge status indicator
- Package contents**
- 1 x microphone, 1 x user manual, 1 x declaration of conformity

#### Technical specifications:

Type:	Wireless set
Weight:	2,97 kg

#### RELACART UR-260D 2-channel UHF Receiver 823-832 + 863-865 MHz

Type:	Receiver
Power supply:	100-240 V AC, 50/60 Hz 12V DC 1000 mA
Power consumption:	Max. 9 W
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Number of channels:	2

Frequency range:	45 - 18000 Hz
S/N ratio:	>100 dB
THD:	<0,5 % at 1 kHz
Network connection:	Protocol: Ethernet TCP/IP via 1x RJ-45 (F) mounting version
DSP:	Digital signal processor 96kHz, 24 bit
Range:	Range up to 80m
Frequency band:	UHF 863 - 865 MHz; UHF 823 - 832 MHz
Diversity:	Antenna diversity
Switching bandwidth:	11 MHz
Frequency stability:	± 0,0005 %
Parallel mode:	Max. 9 transmitter
Modulation:	FM
Frequency selection:	90 switchable frequencies In 10 groups with up to 10 preset frequencies each
Display type:	Multicolor LCD display
Control elements:	Power switch, groundlift selector, menu, navigation keys
Connections:	Antenna via 2 x BNC (F) 8 V Output: microphone via 2 x 3-pin XLR (M) mounting version Output: line via 1 x 6.3 mm plug (unbal.)
Material:	Metal
Color:	Black
PC connect:	RELACART Magic EQ software via RJ-45 (F) mounting version
Housing design:	Desktop console housing (19") 48.3 cm rack installation possible 1 U
Dimensions:	Width: 41 cm Depth: 26 cm Height: 4,3 cm
Weight:	2,40 kg

#### **RELACART UH-222D Microphone 823-832 + 863-865 MHz**

Type:	Hand-held transmitter
Power supply:	3V DC
Capsule type:	Dynamic
Polar pattern:	Super cardoid
Battery:	2 x Mignon (AA) (not included)
Frequency range:	120 - 16000 Hz
Sensitivity:	-53 dB
Max. SPL:	145 dB
Range:	Range up to 80m
Frequency band:	UHF 863 - 865 MHz; UHF 823 - 832 MHz
Switching bandwidth:	11 MHz

RF power output:	10 mW
Modulation:	FM
Frequency selection:	90 switchable frequencies In 10 groups with up to 10 preset frequencies each
Display type:	OLED display
Display:	Charge status indicator , frequency , channel
Control elements:	Gain-switch (high-mid-low), transmitter power switch (high-low)
Switch:	On/off/mute switch
Material:	Aluminum
Dimensions:	Length: 26 cm Diameter: Ø 5,4 cm
Weight:	0,28 kg