

## OMNITRONIC UA-1000 Antenna distributor

Antenna distributor

Art. No.: 13063020

GTIN: 4026397195347



**The article is no longer in our assortment.**

### Features:

- For operating up to four receivers DR-1000 on one pair of multi-antennas
- Replaces the respective antennas and PSUs of the individual receivers
- Up to four antenna distributors UA-1000 can be connected among each other for use of 16 microphones in total
- Low-voltage outputs for supplying four DR-1000, incl. matching connection cables
- Connections for two antenna boosters AB-1000
- All antenna connections via BNC jacks
- Rugged steel housing
- Included in the delivery: 9 BNC connection cables, 2 BNC extension adapters, 4 x 12 V connection cables, 2 rubber antennas

### Logistic

EAN / GTIN: 4026397195347

Weight: 4,05 kg

Length: 0.56 m

Width: 0.33 m

Height: 0.09 m

### Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	100,00 W
Frequency range:	470000000 - 8700000000 Hz
Dimensions:	Width: 48,3 cm Depth: 25 cm Height: 4,45 cm
RF output level:	-0.5 dB to 3 dB
Impedance:	50 ohms

Antenna connectors:	2 x BNC
Receiver outputs:	8 x BNC
Low-voltage outputs:	4 x 12-18 V DC
Dimensions:	482 x 250 x 44 mm
	Rack installation with 1 U
Weight:	2 kg