



**The article is no longer in our assortment.**

### Features:

#### EUROLITE LED KLS-40 Compact Light Set

DMX LED spotlight set with COB LEDs for mobile use

- Complete LED light set with four compact LED spots
- Crossbar with integrated DMX control unit
- Ultra-light ideally suited for mobile use
- Comes pre-assembled
- 1 four color LED per spot (RGBW)
- Movable and tiltable spotlights
- DMX-controlled operation or stand-alone operation with Master/Slave function
- 2, 3, 4, 6, 16, 20 or 24 DMX channels selectable
- Sound-control via built-in microphone, microphone sensitivity adjustable
- Supports QuickDMX - the wireless DMX-system from Eurolite
- Built-in phantom fed socket for QuickDMX receiver (see accessories)
- DMX512 control via regular DMX controller
- Via DMX, each spot can be individually controlled
- Functions: RGBW color mixture, color presets, built-in programs, strobe effect with variable speed, dimmer, sound-control, Master/Slave operation
- Addressing and setting via control panel with 4-digit LED display
- Suited for installation on a speaker stand (not included) or truss
- Black lacquered metal version with movable mounting bracket
- Ideal for bands, stages or solo entertainers
- Switch-mode power supply for operation between 100 and 240 volts
- The device is cooled by passive convection cooling
- Control via stand-alone; DMX; QuickDMX
- Preprogrammed in Light'J; LED PC-Control 512; Light Captain
- Flicker-free

### Logistic

- With a beam angle of 12°

### EUROLITE QuickDMX Wireless receiver phantom-power

Compact wireless DMX receiver 2.4 GHz, phantom powered

- User-friendly 5-pin XLR adapter(female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- Can receive and process up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

#### Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity

### EUROLITE QuickDMX Wireless Transmitter

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR adapter (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can transmit up to 512 DMX channels
- Control via QuickDMX; DMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

#### Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x USB cable

## Technical specifications:

Weight:	3,64 kg
---------	---------

### EUROLITE LED KLS-40 Compact Light Set

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	115 W
IP classification:	IP20
Lamp type:	LED lamp
Cooling:	Passive convection cooling
Control:	Stand-alone; DMX; QuickDMX
Preprogrammed in:	Light J; LED PC-Control 512; Light Captain
Projection:	Flicker-free
Beam angle:	12°

Beam angle (1/2 peak):	12°
Beam angle (1/10 peak):	22°
Housing color:	Black
Dimensions:	Width: 45 cm Depth: 12 cm Height: 18,5 cm
Weight:	3,40 kg
DMX channels:	2/3/4/6/16/20/24
DMX connection:	3-pin XLR
QuickDMX connection:	5-pin XLR
Sound control:	via built-in microphone
LED type:	COB 30 W
Number of LEDs:	4
Beam angle:	12°
Dimensions (L x W x H):	450 x 120 x 185 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting

#### **EUROLITE QuickDMX Wireless receiver phantom-power**

Power supply:	5V DC
IP classification:	IP20
Power connection:	Mains input via 5-pin XLR (W) connector
DMX channels:	Input 512
DMX output:	1 x 5-pin XLR (F)
Control:	DMX; QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz
Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	0,10 kg

#### **EUROLITE QuickDMX Wireless Transmitter**

Power supply:	100-240 V AC, 50/60 Hz 5V DC 1000 mA
IP classification:	IP20
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M)

Control:	QuickDMX; DMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz
Parallel mode:	Max. 6 transmitter
RF power output:	19 dBm
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21,2 cm
	Diameter: Ø 1,8 cm
Weight:	0,15 kg