

## OMNITRONIC Set PM-222 + 2x DD-2520

Set with 2-channel DJ mixer and two turntables

Art. No.: 20000396

GTIN:



**The article is no longer in our assortment.**

### Features:

#### OMNITRONIC PM-222 2-channel DJ Mixer

2-channel DJ mixer

- 2 input channels with gain control, 2-way equalizer and phono/line switching
- DJ microphone input with separate level control
- Pre-fader listening (CUE) to the input channels via adjustable headphones output, with cue mix control
- Replaceable crossfader for crossfading between both channels
- 6-digit stereo LED level meter and master level control
- Outputs: master and record (stereo RCA)
- Desktop console housing
- For application areas such as: Clubs/dancing school; mobile djs / entertainer; installation

#### Package contents

- 1 x user manual, 1 x power cord, 1 x mixer

### Logistic

#### OMNITRONIC DD-2520 USB Turntable bk

Direct-drive DJ turntable with switchable phono/line output

- Built-in USB port and additional phono preamplifier, for a high-quality and convenient digitization of analog vinyl records
- Driver installation not required, unit is identified automatically
- Sampling rates of 44.1 kHz and 48 kHz in stereo, resolution: 16 bits
- Incl. software for recording and editing
- Precision direct drive
- Delivery includes pick-up system
- 2 speeds, pitch control  $\pm 10\%$

- Large start/stop button
- Strobe lamp for exact speed adjustment
- Target lamp
- Delivery includes removable dustcover
- Adjustable anti-skating
- Shock-absorbing feet
- Switchable output phono/line
- USB 1.1 support
- Suitable for Windows XP, Vista, 7 and Mac OS X
- Pitch range:  $\pm 10\%$
- The device can be connected via USB to the PC

#### Package contents

- 1 x system, 1 x turntable platter

## Technical specifications:

Weight: 24,50 kg

### OMNITRONIC PM-222 2-channel DJ Mixer

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	30,00 W
Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>70 dB
THD:	<0,025 % at 1 kHz
Impedance:	Input: microphone 47 kOhm Input: line 47 kOhm Input: phono 47 kOhm
Gain:	Input: variable
Control elements:	Power switch, source selector, crossfader
Status LED:	Master level meter, power
Connections:	Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version Input: line via 4 x stereo RCA Input: phono via 2 x stereo RCA Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input channel: 2 x stereo with line-line-phono switch via RCA, channel control via fader, 2-band tone control EQ, gain control Microphon channel: 1 x mono via jack, channel control via rotary dial, cue mix function Master output: 1 x stereo via RCA, channel control via rotary dial Headphones output: 1 x stereo via jack, channel control via rotary dial

Max. level:	Output: master +19 dBu
Housing design:	Desktop console housing
Dimensions:	Width: 19 cm Depth: 26 cm Height: 13,7 cm
Weight:	2,00 kg

#### OMNITRONIC DD-2520 USB Turntable bk

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	12,00 W
Power connection:	Fixed power supply cord with Euro plug
Frequency range:	20 - 20000 Hz
Drive type:	Direct drive Brushless DC motor
Drive:	Initial torque: 1 kg/cm Start time: 1 sec. Stop time: 1 sec. Speed change time: <1s 1kHz 5cm/sec
Wow and flutter:	<0,15 % WRMS
Rumble:	55 dB DIN B
Speed:	33 RPM; 45 RPM
Tone arm:	S-shape with Cardan"s suspension Length: 230 Overhang: 16 mm Stylus pressure: 0-4 g, adjustable
Output level:	Phono 1,5-3,6 mV/ 1 kHz 5 cm/sec Line 90-216 mV/ 1 kHz 5 cm/sec
Connections:	Output: line/phono via stereo RCA Output: USB B (F) mounting version
Pitch range:	±10%
USB port:	1 x USB 1.1, type B
Color:	Black
PC connect:	Via USB
Dimensions:	Width: 45 cm Depth: 35 cm Height: 15,5 cm
Weight:	11,25 kg
Turntable platter	
Dimensions:	Diameter: Ø 33 cm