

EUROLITE Set 2x Stage Panel 32 + Color Chief + QuickDMX transmitter + 2x receiver 486

Stage panel set with 2x light effect bar, DMX lighting desk, transmitter and 2x receiver

GTIN:



The article is no longer in our assortment.

Features:

EUROLITE Stage Panel 32 HCL LED

Light effect bar with RGBAW+UV color mixing, with 5-pin QuickDMX connector

- 32 high-power 10 W RGBAW+UV LEDs (6in1)
- 8 segments for dynamic running lights
- Built-in auto and music show programs
- Direct color selection for 26 preset colors
- Variable color temperature 2700-8000 K
- Stepless color blend, color change, color fade, dimmer and strobe effect
- 4 barn doors to avoid blinding the audience and for protection during transport
- Control panel with LED display for easy configuration
- Convenient wireless control via included IR remote control
- Supports QuickDMX - the wireless DMX system from Eurolite
- Built-in phantom-powered socket for QuickDMX receivers (optional)
- Swivel mounting bracket
- Additional bracket for floor use
- Mains input and output for power linking up to 8 units
- 32 powerful LEDs 10 W high-power 6in1 HCL RGBWA/UV (homogenous color mix)
- Strobe effect; UV effect
- The device is cooled by cooling fan
- Control via stand-alone; DMX; IR remote control; Sound to light via Microphone; QuickDMX via 5-pin XLR (M) mounting version (optional); Master/slave function
- Preprogrammed in Light J; LED PC-Control 512; EASY SHOW 1; LED EASY OPERATOR 4x6; LED EASY OPERATOR DELUXE; Light Captain
- Flicker-free
- With a beam angle of 16°

Package contents

Logistic

- 1 x remote control

EUROLITE DMX LED Color Chief Controller

DMX lighting desk with innovative control concept for LED spotlights

- Easy control of LED spotlights with up to 6 colors, light bars as well as simple lighting effects
- For 8 devices or device groups, each with up to 4 segments
- Quick and easy programming
- Additional fixtures can be configured manually
- 8 color effects directly selectable
- 3 additional channels available per fixture (e.g. for rotations)
- Color wheel selection and simulation
- 24 memory spaces for scenes and chases
- Several chases and scenes can be run simultaneously
- USB port for storing program data
- Sound control via audio signal or TAP button
- Master dimming, fade time and run time easily adjustable
- Programmable 24 scenes/chases distributed over 1 page(s)
- Can transmit up to 240 DMX channels
- Control via DMX; Sound to light via RCA (F) mounting version; Sound to light via Microphone
- (19") 48.3 cm rack installation 3 U
- Desktop console housing
- For application areas such as: Clubs/dancing school; Party room; Trade fair and shop fitting; mobile djs / entertainer; restaurants, bars and hotels
- Silent operation
- Firmware can be updated

Package contents

- 1 x controller, 1 x user manual, 1 x external mains adapter

EUROLITE QuickDMX Wireless Transmitter

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR adapter (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can transmit up to 512 DMX channels
- Control via QuickDMX; DMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity, 1 x external mains adapter, 1 x USB cable

EUROLITE QuickDMX Wireless receiver phantom-power

Compact wireless DMX receiver 2.4 GHz, phantom powered

- User-friendly 5-pin XLR adapter(female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- Can receive and process up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Package contents

- 1 x device, 1 x user manual, 1 x declaration of conformity

Technical specifications:

Weight: 19,88 kg

EUROLITE Stage Panel 32 HCL LED

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	100 W
IP classification:	IP20
Power connection:	Mains input via P-Con (blue), mounting version power supply cord with safety plug (provided)
Power output:	1 x P-Con (gray), mounting version
Lamp type:	LED lamp
LED:	32 x 10 W high-power 6in1 HCL RGBWA/UV (homogenous color mix)
Flash rate:	0 - 20 Hz
DMX channels:	3; 5; 6; 13; 48; 52
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Cooling:	Cooling fan
Control:	Stand-alone; DMX; IR remote control; Sound to light via Microphone; QuickDMX via 5-pin XLR (M) mounting version (optional); Master/slave function
Preprogrammed in:	Light J; LED PC-Control 512; EASY SHOW 1; LED EASY OPERATOR 4x6; LED EASY OPERATOR DELUXE; Light Captain
Projection:	Flicker-free
Beam angle:	16°
Beam angle (1/2 peak):	16°
Beam angle (1/10 peak):	35°
Housing color:	Black
Dimensions:	Width: 50 cm Depth: 9,3 cm Height: 29,5 cm
Weight:	8,65 kg
Photobiological safety:	Risk Group 0
Remote control	
Battery:	1 x Button cell 3.0 V CR2025 lithium manganese built-in
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting

EUROLITE DMX LED Color Chief Controller

Power supply:	100-240 V AC, 50/60 Hz 9 V DC 800 mA
Power consumption:	10 W
IP classification:	IP20
Power connection:	Mains input via Coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Programs:	Programmable 24 scenes/chases distributed over 1 page(s)
DMX channels:	Output 240
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; Sound to light via RCA (F) mounting version; Sound to light via Microphone
Housing color:	Black
Available storage media:	USB devices (FAT 32)
USB port:	Typ A
Color:	Black
PC connect:	, firmware can be updated
Housing design:	(19") 48.3 cm rack installation 3 U Desktop console housing
Dimensions:	Width: 48,3 cm Depth: 13,35 cm Height: 8,5 cm
Weight:	2,25 kg
Noise classification:	Class 0 (no noise at all)

EUROLITE QuickDMX Wireless Transmitter

Power supply:	100-240 V AC, 50/60 Hz 5 V DC 1 A
IP classification:	IP20
Power connection:	Mains input via Coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M)
Control:	QuickDMX; DMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz
Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm

Weight: 150 g

EUROLITE QuickDMX Wireless receiver phantom-power

Power supply:	5 V DC
IP classification:	IP20
Power connection:	Mains input via 5-pin XLR (W) connector
DMX channels:	Input 512
DMX output:	1 x 5-pin XLR (F)
Control:	DMX; QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2,4 GHz
Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	100 g
