

## EUROLITE Set 2x KLS-180 + Color Chief + QuickDMX transmitter + 2x receiver No.: 20000487

Compact light set with 2x KLS 180, DMX lighting desk, transmitter and 2x receiver

GTIN:



**List price: 891.31 €**

incl. 19% VAT.

### Features:

#### EUROLITE LED KLS-180 Compact Light Set

Bar with 4 RGBW spots and 4 white strobe LEDs, with QuickDMX connector (XLR)

- Crossbar with integrated DMX control unit and stand sleeve
- Ultra-light ideally suited for mobile use
- Ideal for bands, stages or solo entertainers
- Suited for installation on a speaker stand (not included) or truss
- Comes pre-assembled with practical transport bag
- 4 powerful 4in1 LEDs per spot provide for an exquisite RGBW color mix
- Strobe effect with 4 white 1 W LEDs
- Movable and tiltable spotlights
- Via DMX, each spot can be individually controlled
- DMX-controlled operation or stand-alone operation with Master/Slave function
- Supports QuickDMX - the wireless DMX-system from Eurolite
- Built-in phantom fed socket for QuickDMX receiver (see accessories)
- Functions: RGBW color mixture, color presets, built-in programs, strobe effects with variable speed, dimmer, Master/Slave operation
- Addressing and setting via control panel with 4-digit LED display
- Additional controlling possibility via the EUROLITE IR-7 remote control, included in delivery
- Black lacquered metal version with movable mounting bracket
- IEC terminals for power linking up to 8 units
- LED: Spot 4 x separate controlling each with 4 x high-power 8 W 4in1 QCL RGBW (homogenous color mix)
- LED: Strobe effect separate controlling 4 x high-power 1 W CW
- Can be operated in 3; 4; 8; 21 CH mode
- The device is cooled by passive convection

### Logistic

- Controlling by Stand-alone; DMX; IR remote control; Sound to light via Microphone; QuickDMX via 5-pin XLR (M) mounting version (optional)
- Is in EASY SHOW; EUROLITE LED PC-Control 512 software already preprogrammed
- Flicker-free projection

### **EUROLITE DMX LED Color Chief Controller**

DMX lighting desk with innovative control concept for LED spotlights

- Easy control of LED spotlights with up to 6 colors, light bars as well as simple lighting effects
- For 8 devices or device groups, each with up to 4 segments
- Each device can occupy up to 30 channels
- Quick and easy programming
- Eurolite KLS systems and LED spotlights already in the library
- Additional fixtures can be configured manually
- 8 color effects directly selectable
- 3 additional channels available per fixture (e.g. for rotations)
- Color wheel selection and simulation
- 24 memory spaces for scenes and chases
- Several chases can be run simultaneously
- USB port for data storage of lighting programs
- Sound control via audio signal or TAP button
- Master dimming, fade time and run time easily adjustable
- 3-pin XLR connector
- Firmware update via USB
- Desktop console
- Programmable 24 sequencens
- Can transmit up to 240 DMX channels
- Controlling by DMX; Sound to light via RCA (f) mounting version; Sound to light via Microphone
- (19") 48.3 cm rack installation 3 U

### **EUROLITE QuickDMX Wireless Transmitter**

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR plug (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transmitters and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Simultaneous operation of up to 6 transmitters, thus control of 3072 DMX channels (6 DMX universes) possible
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- Plug & Play: quick and easy setup with one operating button for connecting/disconnecting QuickDMX receivers
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Powered via included PSU
- 2.4 GHz ISM band - license-free worldwide
- Can transmit up to 512 DMX channels
- Controlling by QuickDMX built-in; DMX
- Use a operating range up to 400m

### **EUROLITE QuickDMX Wireless receiver phantom-power**

Compact wireless DMX receiver 2.4 GHz, phantom powered

- User-friendly 5-pin XLR plug (female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX receivers and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- Plug & Play: quick and easy setup with one operating button for connecting/disconnecting QuickDMX receivers
- LED indication for functions
- Transceiver, to be used as transmitter or receiver

- Requires 5 V phantom power for operation
- 2.4 GHz ISM band - license-free worldwide
- Can receive and process up to 512 DMX channels
- Controlling by DMX; QuickDMX built-in
- Use a operating range up to 400m

## Technical specifications:

---

Weight: 12,28 kg

---

### EUROLITE LED KLS-180 Compact Light Set

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	80 W
IP classification:	IP20
Power connection:	Mains input IEC connector (M) mounting version Power supply cord with safety plug (provided)
Power output:	1 x IEC connector (F) mounting version
Lamp type:	LED lamp
LED:	Spot 4 x high-power 8 W 4in1 QCL RGBW (homogenous color mix) Strobe effect 4 x high-power 1 W CW
DMX channels:	3; 4; 8; 21
DMX input:	3-pin XLR (M) mounting version
DMX output:	3-pin XLR (F) mounting version
Cooling:	Passive convection
Control:	Stand-alone; DMX; IR remote control; Sound to light via Microphone; QuickDMX via 5-pin XLR (M) mounting version (optional); EASY SHOW; EUROLITE LED PC-Control 512 software
Beam angle:	9°
Beam angle (1/2 peak):	9°
Beam angle (1/10 peak):	18°
Housing color:	Black
Display type:	4 digits 7-segment LED display
Dimensions:	Width: 60,5 cm Depth: 14 cm Height: 23 cm
Weight:	4,85 kg
Noise classification:	Class 0 (no noise at all)
Remote control	
Battery:	1 x Button cell 3.0 V CR2025 lithium manganese built-in
Legal specifications	
Special product:	Not designed for household room illumination
intended use:	show effect lighting

### **EUROLITE DMX LED Color Chief Controller**

Power supply:	100-240 V AC, 50/60 Hz 9 V DC 800 mA
Power consumption:	10 W
IP classification:	IP20
Power connection:	Mains input Coaxial power connector (M) Power supply cord with AC adapter (provided)
Programs:	Programmable 24 Sequences
DMX channels:	Output 240
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; Sound to light via RCA (f) mounting version; Sound to light via Microphone
Housing color:	Black
Available storage media:	USB devices (FAT 32)
USB port:	Typ A
Color:	Black
Housing design:	(19") 48.3 cm rack installation 3 U
Dimensions:	Width: 48,3 cm Depth: 13,35 cm Height: 8,5 cm
Weight:	2,25 kg

### **EUROLITE QuickDMX Wireless Transmitter**

Power supply:	100-240 V AC, 50/60 Hz 5 V DC 1 A
IP classification:	IP20
Power connection:	Mains input Coaxial power connector (M) Power supply cord with AC adapter (provided)
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M)
Control:	QuickDMX built-in; DMX
Carrier frequency:	2,4 GHz
Modulation:	GFSK
Parallel mode:	Max. 6 transmitter
Range:	400 m
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	150 g

### **EUROLITE QuickDMX Wireless receiver phantom-power**

Power supply:	5 V DC
IP classification:	IP20
Power connection:	Mains input 5-pin XLR (W) connector
DMX channels:	Input 512
DMX output:	1 x 5-pin XLR (F)
Control:	DMX; QuickDMX built-in
Carrier frequency:	2,4 GHz
Modulation:	GFSK
Parallel mode:	Max. 6 transmitter
Range:	400 m
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	100 g