

EUROLITE Set QuickDMX 1x transmitter + 6x receiver

Wireless DMX transmitter including 6x compact wireless DMX receiver

Art. No.: 2000647

GTIN: 4026397009798



List price: 534.31 €

incl. 19% VAT.

Features:

EUROLITE QuickDMX Wireless Transmitter

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR plug (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transmitters and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Simultaneous operation of up to 6 transmitters, thus control of 3072 DMX channels (6 DMX universes) possible
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- Plug & Play: quick and easy setup with one operating button for connecting/disconnecting QuickDMX receivers
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Operation via included power adapter
- 2.4 GHz - license-free worldwide
- Can transmit up to 512 DMX channels
- Controlling by QuickDMX built-in; DMX
- Use a operating range up to 400m

EUROLITE QuickDMX Wireless Receiver

Compact wireless DMX receiver 2.4 GHz

- User-friendly 3-pin XLR plug (female) with swivel antenna

Logistic

EAN / GTIN: 4026397009798

Weight: 1,60 kg

Length: 0.30 m

Width: 0.22 m

Height: 0.21 m

- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX receivers and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- Plug & Play: quick and easy setup with one operating button for connecting/disconnecting QuickDMX receivers
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Operation via included power adapter
- 2.4 GHz - license-free worldwide
- Can receive and process up to 512 DMX channels
- Controlling by QuickDMX built-in
- Use a operating range up to 400m

Technical specifications:

Weight: 1,10 kg

EUROLITE QuickDMX Wireless Transmitter

Power supply:	100-240 V AC, 50/60 Hz 5 V DC 1 A
IP classification:	IP20
Power connection:	Mains input via Coaxial power connector (M) power supply cord with AC adapter (provided)
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M)
Control:	QuickDMX built-in; DMX
Carrier frequency:	2,4 GHz
Modulation:	GFSK
Parallel mode:	Max. 6 transmitter
Range:	400 m
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	150 g

EUROLITE QuickDMX Wireless Receiver

Power supply:	100-240 V AC, 50/60 Hz
IP classification:	IP20
Power connection:	Mains input via Coaxial power connector (M) power supply cord with AC adapter (provided)
DMX channels:	Input 512
DMX output:	3-pin XLR (F)
Control:	QuickDMX built-in
Carrier frequency:	2,4 GHz

Modulation:	GFSK
Parallel mode:	Max. 6 transmitter
Range:	400 m
Color:	Silver
Dimensions:	Length: 21,2 cm Diameter: Ø 1,8 cm
Weight:	160 g