

OMNITRONIC CPE-40P PA Mixing Amplifier

PA mono mixing amplifier with MP3 player and IR remote control, Bluetooth, 40 watts

Art. No.: 80709605

GTIN: 4026397683141



List price: 148.75 €

incl. 19% VAT.

Features:

- PA outputs for 70 V or 100 V PA speakers
- PA outputs for low-impedance speakers (4-16 ohms)
- Integrated Bluetooth audio streaming
- SD card slot and USB port
- FM tuner with auto scan
- 3 microphone inputs with separate level controls
- Mic 1 with phantom power and priority circuit
- Mic 2 and 3 switchable mic/line
- 2 line inputs with separate level controls
- 1 line output
- Treble and bass and master controls for the output signal
- 4-digit LED level meter
- Protection circuits with LED indication: overload, short circuit, clip limiter, overheat
- Mains operation and 24 V emergency power operation
- Controlling by Bluetooth; IR remote control
- 2 U
- Desktop console housing

Package contents

- 1 x Amplifier, 1 x User manual, 1 x Declaration of conformity, 1 x Power cord, 1 x Antenna, 1 x Remote control, 1 x Battery

Logistic

EAN / GTIN: 4026397683141

Weight: 3,00 kg

Length: 0.35 m

Width: 0.27 m

Height: 0.14 m

Technical specifications:

Power supply: 230 V AC, 50 Hz
Or

	24 V
Power consumption:	80 W
Output power:	40 W RMS
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug included
Impedance:	1 x 4 ohms; 1 x 8 ohms; 1 x 16 ohms; 1 x Public address systems 100V
Control:	Bluetooth; IR remote control
Audio player:	USB + SD + Bluetooth + FM Radio
Circuitry:	Class D
Equalizer:	Master: 1 x 2-band tone control
Connections:	Input: Microphone via 1 x 3-pin XLR Input: mic/line via 2 x 6.3 mm jack socket (stereo) mounting version Input: line via 2 x stereo RCA Output: line via 1 x stereo RCA 0,774 V Output: speaker via screw terminal
Format:	MP3
Housing design:	2 U Desktop console housing
Dimensions:	Width: 30,3 cm Depth: 22 cm Height: 9,1 cm
Weight:	2,73 kg
Remote control	
Battery:	1 x button cell CR2025 Button cell 3.0 V CR2025 lithium manganese built-in