

## OMNITRONIC LS-622A Powered Live Mixer

Amplificateur de mixage live à 6 canaux avec 2 x 150 W/4 ohms

Réf. : 10060050

GTIN: 4026397183306



### Caractéristiques:

- Low-noise 6-channel Mic/Line mixer
- 2 mono inputs with XLR sockets, +48V phantom power and balanced line inputs
- Insert or Direct Out for every mono channel
- 2 stereo inputs via balanced jacks
- Integrated effect unit with 9-level echo
- 3-band EQ for all inputs
- Peak LED per mono input
- Aux send per channel for controlling external effectors
- Aux return with balanced 6.3 mm jack socket
- Separate Main Mix, Group and headphones outputs
- Tape inputs and outputs
- 7-band equalizer for fine-tuned sound
- Precise 10-fold stereo LED meter
- Output power 2 x 150 W/4 ohms
- Processeur de signal numérique

### Logistique

EAN / GTIN: 4026397183306

Poids: 10,20 kg

Longueur: 0.47 m

Largeur: 0.43 m

Hauteur: 0.24 m

### Données techniques:

Alimentation électrique:	115/230 V CA, 50/60 Hz
Puissance totale de raccordement:	500,00 W
Puissance de sortie:	Max. 300 W 150 W RMS (4 Ohm)

Branchement électrique:	Alimentation électrique via appareils froids (M) version encastrable câble d'alimentation à prise contact de protection (inclus dans la livraison)
	Tramite
Plage de fréquence:	10 - 60000 Hz microphone 10 - 60000 Hz Mono 10 - 55000 Hz Stéréo
Rapport signal/bruit:	>112 dB
Distorsion harmonique:	<0,01 % avec 1 kHz
DSP:	Processeur de signal numérique
Commutation:	Class AB
Égaliseur:	Master: 1 x égaliseur graphique 7 bandes Stéréo
Dimension:	Largeur : 33 cm Profondeur : 39 cm Hauteur : 12,5 cm
Poids:	8,40 kg
Inputs:	
2 mono	XLR or balanced 6.3 mm jacks
2 inserts	6.3 mm jacks
2 stereo	balanced 6.3 mm jacks
1 Aux-Return	balanced 6.3 mm jacks
Tape In	RCA
Outputs:	
1 Main Out:	XLR or balanced 6.3 mm jacks
1 Headphone	balanced 6.3 mm jack
1 Aux Send:	balanced 6.3 mm jack
2 Direct Out	6.3 mm jacks
Tape Out	RCA
Tone control/channel:	
Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Power output sine:	
Stereo 4 ohms	2 x 150 W

## Contenu de la livraison: