

OMNITRONIC LS-822A Powered Live Mixer

Amplificateur de mixage live à 8 canaux avec 2 x 200 W/4 ohms

Réf. : 10060100

GTIN: 4026397183313



Caractéristiques:

- Low-noise 8-channel Mic/Line-mixer
- 4 mono inputs with XLR sockets, +48V phantom power and balanced line inputs
- Insert or Direct Out for every mono channel
- 2 stereo inputs via balanced jacks
- Integrated effect unit with 9-level echo
- 3-band EQ for all inputs
- Peak LED per mono input
- Aux send per channel for controlling external effectors
- Aux return with balanced 6.3 mm jack socket
- Separate Main Mix, Group and headphones outputs
- Tape inputs and outputs
- Precise 10-digit LED meter
- Output power 2 x 200 W/4 ohms
- Processeur de signal numérique

Logistique

EAN / GTIN: 4026397183313

Poids: 11,20 kg

Longueur: 0.48 m

Largeur: 0.47 m

Hauteur: 0.23 m

Données techniques:

Alimentation électrique:	115/230 V CA, 50/60 Hz
Puissance totale de raccordement:	800,00 W
Puissance de sortie:	Max. 400 W 200 W RMS (4 Ohm)

Branchement électrique:	Alimentation électrique via appareils froids (M) version encastrable câble d'alimentation à prise contact de protection (inclus dans la livraison)
	Tramite
Plage de fréquence:	10 - 60000 Hz microphone 10 - 60000 Hz Mono 10 - 55000 Hz Stéréo
Rapport signal/bruit:	>112 dB
Distorsion harmonique:	<0,01 % avec 1 kHz
DSP:	Processeur de signal numérique
Commutation:	Class AB
Égaliseur:	Master: 1 x égaliseur graphique 7 bandes Stéréo
Dimension:	Largeur : 39 cm Profondeur : 39 cm Hauteur : 15 cm
Poids:	9,45 kg
Inputs:	
4 mono	XLR or balanced 6.3 mm jacks
4 inserts	6.3 mm jacks
2 stereo	balanced 6.3 mm jacks
1 Aux-Return	balanced 6.3 mm jack
Tape In	RCA
Outputs:	
1 Main Out:	XLR or balanced 6.3 mm jacks
1 Headphone	balanced 6.3 mm jack
1 Aux Send:	balanced 6.3 mm jack
4 Direct Out	6.3 mm jacks
Tape Out	RCA
Tone control/channel:	
Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Power output sine:	
Stereo 4 ohms	2 x 200 W

Contenu de la livraison: