

## OMNITRONIC MCS-1250 12-channel amplifier

Amplificateur audio à 6 canaux avec affectation matricielle 12 x 50 W/4 ohms

Réf. : 10452491

GTIN: 4026397309645



### Description:

Amplifier of unlimited possibilities!  
Perhaps the MCS-1250's possibilities are not unlimited, but they are definitely numerous. Let's take a look at a locality that consists of several rooms for instance. Now, each room should have its own music, but due to space problems, only a compact and centrally located amplifier unit can be installed. Not an issue. The MCS-1250 offers the possibility to operate six zones simultaneously. Each zone is equipped with a controller that is able to separate the zones and to adjust them individually. So the volume, the basses and the heights can be set as required. Really a nice one!

### Caractéristiques:

- 12 x 50 W/4 ohms
- Ideal for multi-zone applications
- 6 stereo inputs expandable to 18 stereo zones with further units
- Matrix input assignment: input sources are freely assignable to each channel
- Volume, Treble, Bass adjustment with controller MCS-1250R for each output individually
- Incl. IR remote control
- Incl. 6 controllers MCS-1250R
- Signal inputs via stereo RCA sockets
- Signal outputs via terminal blocks
- Bridged switch for bridging
- LED indicators on the front panel
- Rack installation

### Logistique

EAN / GTIN: 4026397309645

Poids: 1,70 kg

Longueur: 0.27 m

Largeur: 0.24 m

Hauteur: 0.13 m

## Données techniques:

---

Alimentation électrique:	115/230 V CA, 50/60 Hz
Puissance totale de raccordement:	1250,00 W
Puissance de sortie:	Max. 600 W
Plage de fréquence:	20 - 20000 Hz
Dimension:	Largeur : 48,3 cm Profondeur : 42 cm Hauteur : 8,9 cm
Poids:	11,25 kg
Batterie:	2 x pile bouton 3,0 V CR2025 lithium manganèse intégré
Output power sine:	
Stereo 4 ohms:	12 x 50 W
Stereo 8 ohms:	12 x 25 W
8 ohms bridged:	6 x 100 W
Distortion:	0.01 % (1 kHz)
S/N ratio:	85 dB
Input sensitivity:	250 mV
Input impedance:	>47 kohms
Zone input connectors:	6 x stereo RCA
Link:	RS-232
Zone output connectors:	Terminal blocks
Controller connector:	RJ45
LED indicators (per channel):	Signal
Dimensions:	482 x 420 x 102 mm

## Contenu de la livraison:

---

1 x télécommande