

## OMNITRONIC MX-540 Multichannel mixer

PRO 5+1-channel mixer

Art.n.: 10006760

GTIN: 4026397361193



**L'articolo non è più disponibile.**

### Features :

- High-grade discotheque mixer with convincing sound and 3 master channels
- 5 channels with gain control, 3-band equalizer, cue button, smooth and durable faders and 10-digit LED level meter
- 1 DJ microphone channel with 3-band equalizer, level control, on air and talkover selector
- Color illuminated rotary controls and rubber buttons
- Prefader listening to all input channels and the master output via adjustable headphones output, with cue mix/split function
- Replaceable crossfader for crossfading between input channels, with assignment switches and fader start function
- 3 separately controllable master channels with mono/stereo selector switch
- Master channel 1 with fader and 10-digit stereo LED level meter, switchable to master channel 2
- Adjustable monitor output (DJ booth)
- 2 recording outputs, independent of the master and with on/off switch for DJ microphone signals
- Inputs: 12 x line (stereo RCA), additionally 1 x line at the front panel (stereo RCA/3.5 mm jack (1/8")); 3 x phono/line (stereo RCA), switchable; 1 x DJ microphone (XLR/6.3 mm jack), 3 x microphone (6.3 mm jack) and headphones (3.5 mm/6.3 mm jack (1/8"/1/4"))
- Outputs: 2 x master (stereo XLR/stereo RCA), 1 x master (stereo RCA/6.3 mm stereo jack, bal.), booth (stereo RCA) and 2 x record (stereo RCA)
- Operation via supplied power unit
- Available in silver or black
- Rack installation, 5 U
- Montaggio su rack (19") 48,3 cm

### Logistica

EAN / GTIN: 4026397361193

Peso : 6,10 kg

Lunghezza : 0.61 m

Larghezza : 0.27 m

Altezza : 0.15 m

## Dati tecnici :

|                               |                                                            |
|-------------------------------|------------------------------------------------------------|
| Potenza totale installata:    | 30,00 W                                                    |
| Intervallo di frequenza:      | 20 - 20000 Hz                                              |
| Struttura della custodia:     | Montaggio su rack (19") 48,3 cm                            |
| Misure:                       | Larghezza: 48,3 cm<br>Profondità: 22 cm<br>Altezza: 8,9 cm |
| Peso:                         | 5,55 kg                                                    |
| Power supply:                 | 230 V AC, 50 Hz,<br>via supplied power unit                |
| Inputs:                       |                                                            |
| DJ microphone (front):        | combined XLR/6.3 mm jack (1/4") (bal.)                     |
| DJ microphone (rear):         | 6.3 mm jack (1/4") (bal.)                                  |
| MIC 1-3:                      | 6.3 mm jack (1/4") (bal.)                                  |
| Minimum input voltage:        | 1 mV RMS                                                   |
| LINE 1-12 (rear):             | stereo RCA                                                 |
| LINE 10 (front):              | stereo RCA/3.5 mm jack (1/8")                              |
| Minimum input voltage:        | 150 mV RMS                                                 |
| PHONO 1-3:                    | stereo RCA                                                 |
| Minimum input voltage:        | 3 mV RMS                                                   |
| Outputs:                      |                                                            |
| MASTER 1.2:                   | stereo XLR/stereo RCA                                      |
| Output voltage:               | 0.75 V/1.5 V RMS (switchable)                              |
| MASTER 3:                     | stereo RCA/6.3 mm stereo jack                              |
| Output voltage:               | 0.75 V                                                     |
| BOOTH:                        | stereo RCA                                                 |
| Output voltage:               | 0.75 V                                                     |
| REC:                          | stereo RCA                                                 |
| Output voltage:               | 0.75 V                                                     |
| Headphones output:            | 3.5 mm/6.3 mm jack (1/8"/1/4") (min. 8 ohms)               |
| X-FADER START:                | 2 x 3.5 mm jack (1/8")                                     |
| Tone control (DJ microphone): |                                                            |
| 1 x High:                     | -12 dB to +12 dB/ 10 kHz, $\pm 1$ dB                       |
| 1 x Middle:                   | -12 dB to +12 dB/ 1 kHz, $\pm 1$ dB                        |
| 1 x Low:                      | -12 dB to +12 dB/ 100 Hz, $\pm 1$ dB                       |
| Talkover attenuation:         | -15 dB                                                     |
| Tone control (channel 1-5):   |                                                            |
| 5 x High:                     | -26 dB to +12 dB/ 10 kHz, $\pm 1$ dB                       |
| 5 x Middle:                   | -26 dB to +12 dB/ 1 kHz, $\pm 1$ dB                        |
| 5 x Low:                      | -26 dB to +12 dB/ 100 Hz, $\pm 1$ dB                       |
| S/N ratio:                    | >75 dB                                                     |
| Distortion:                   | 0.03%                                                      |

Dimensions (WxHxD):482 x 220 x 110 mm (19", 5 U)

---