



USB MP3

OMNITRONIC PM-211P DJ mixer with player
2-channel DJ mixer (with built-in MP3 player)

- Adjustable MP3 player for external USB storage media up to 32 GB, e.g. USB flash drives or portable players
- 2 input channels with gain control and phono/line switching
- DJ microphone input with talkover selector, level and tone control
- Adjustable front aux input for portable music players
- Pre-fader listening (CUE) to the input channels via adjustable headphones output, with cue mix control



No. 10006873

Technical specifications:

Power supply:	230 V AC, 50 Hz ~
	via supplied power unit
Power consumption:	3 W
USB port:	USB type A
Available storage media:	USB devices up to 32 GB (FAT32)
Playback format:	MP3, WAV
Inputs:	
Line/phono:	2 x stereo RCA
DJ microphone:	6.3 mm jack, unbal.
Outputs:	
Master:	stereo RCA
Record:	stereo RCA
Headphones:	6.3 mm stereo jack (min. 32 ohms)
Frequency range:	20-20000 Hz
S/N ratio:	>75 dB
Distortion:	<0.07 %
Dimensions (LxWxH):	180 x 140 x 65 mm
Weight:	1.2 kg

USB MP3

OMNITRONIC PM-311P DJ mixer with Player
3-channel DJ mixer (with built-in MP3 player)

- 3 input channels, switchable 2 x phono/line and 1 x USB/line
- MP3 player for external USB storage media up to 32 GB, e.g. USB flash drives or portable players
- DJ microphone input with talkover selector, level control and 3-band equalizer
- Pre-fader listening (CUE) to the input channels and the master output via adjustable headphones output, with cue mix control



No. 10006879

Technical specifications:

Power supply:	230 V AC, 50 Hz ~
	via supplied power unit
Power consumption:	4 W
USB port:	USB type A
Available storage media:	USB devices up to 32 GB (FAT32)
Playback format:	MP3, WAV
Inputs:	
Line/phono:	2 x stereo RCA
Line:	stereo RCA
DJ microphone:	6.3 mm jack, unbal.
Outputs:	
Master:	stereo RCA
Record:	stereo RCA
Headphones:	6.3 mm stereo jack (min. 32 ohms)
Frequency range:	20-20000 Hz
S/N ratio:	>75 dB
Distortion:	<0.07 %
Dimensions (LxWxH):	260 x 172 x 78 mm
Weight:	1.5kg