

NEW PCconnect MIDI USB

No. 11045060

**OMNITRONIC CMX-2000 2+1-channel MIDI controller**  
 Digital DJ mixer and controller incl. Virtual DJ 7 LE + DJ One Start software

- 2-channel DJ mixer and MIDI controller with built-in USB (4-channel) soundcard
- Designed for Virtual DJ, Traktor and Serato Scratch Live
- Flexible routing for analog inputs and MIDI decks
- Built-in DVS audio system for vinyl/CD timecode systems
- Adjustable curves and reverse selectors for crossfader and channel faders
- 3-band EQ and LPF/HPF filter

**Technical specifications:**

Power supply:	100-240 V AC, 50/60 Hz –
Power consumption:	14 W
Inputs:	
Line:	2 x stereo RCA
Line/phone:	2 x stereo RCA, switchable
DJ microphone:	combination XLR/6.3 mm jack, bal.
Aux:	3.5 mm jack and stereo RCA
Outputs:	
Master:	XLR L/R and stereo RCA
Booth:	stereo RCA
Headphones:	3.5 mm and 6.3 mm jack
USB port:	2.0, type B
Converter:	16 bits
Sample rate:	48 kHz
Faderstart:	2 x 3.5 mm jack
Dimensions:	360 x 265 x 105 mm
Weight:	4 kg



one

