



**The article is no longer in our assortment.**

### Features:

#### EUROLITE LED FE-Bar RGBAW light set

RGBAW flower effect bar with 1 W LEDs

- Equipped with 20 x 1 W LED in red, green, blue, amber and white
- DMX512 control via regular DMX controller (occupies 8 channels)
- The colorful flower beams change their direction of movement at every bass beat in sound controlled mode
- Sound controlled via built-in microphone
- Microphone sensitivity adjustable via rotary control
- Internal programs
- Master/Slave function
- Control panel with 3 buttons and LED display
- Rugged compact housing
- Ready for connection via enclosed IEC power cord with safety plug
- Mounting bracket and mounting hole (36 mm) with fixation screw for installation on a truss system or stand
- Preprogrammed in Light'J

### Logistic

#### EUROLITE RC-2 remote control 10m

Simple remote control

- Suitable for EUROLITE LED MAT-Bar 4x 64 RGB DMX
- For controlling the blackout in stand-alone mode
- For switching the internal programs, strobe and speed
- Adjustable reaction time for sound control
- 10 m connection cable with stereo jack

## Technical specifications:

---

Weight:	6,33 kg
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting

### EUROLITE LED FE-Bar RGBAW light set

Power supply:	230 V AC, 50 Hz
Power consumption:	50,00 W
Preprogrammed in:	Light´J
Dimensions:	Width: 80 cm Depth: 20 cm Height: 19 cm
Weight:	5,70 kg
DMX channels:	8
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
LED type:	1 W
LED number:	20
Beam angle:	40°
Mounting hole:	D = 36 mm
Dimensions (L x W x H):	800 x 200 x 190 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting