

## **OMNITRONIC PM-222 2-channel DJ Mixer**

2-channel DJ mixer











# List price: 129.71 €

incl. 19% VAT.

#### Features:

- 2 input channels with gain control, 2-way equalizer and phono/line switching
- DJ microphone input with separate level control
- Pre-fader listening (CUE) to the input channels via adjustable headphones output, with cue mix control
- Replaceable crossfader for crossfading between both channels
- 6-digit stereo LED level meter and master level control
- Outputs: master and record (stereo RCA)
- Desktop console housing
- For application areas such as: Clubs/dancing school; mobile djs / entertainer; installation Package contents
- 1 x user manual, 1 x power cord, 1 x mixer

### **Technical specifications:**

100-240 V AC, 50/60 Hz
30,00 W
Protection class II
Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
20 - 20000 Hz
>70 dB

#### Logistic

EAN / GTIN: 4026397380392 Weight: 2,35 kg Length: 0.31 m Width: 0.23 m Heigth: 0.17 m

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

THD:	<0,025 % at 1 kHz
Impedance:	Input: microphone 47 kOhm
	Input: line 47 kOhm
	Input: phono 47 kOhm
Gain:	Input: variable
Control elements:	Power switch, source selector, crossfader
Status LED:	Master level meter, power
Connections:	Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version
	Input: line via 4 x stereo RCA
	Input: phono via 2 x stereo RCA
	Output: master via 1 x stereo RCA
	Output: rec. via 1 x stereo RCA
	Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input chanel: 2 x stereo with line-line-phono switch via RCA, channel control via fader, 2-band tone control EQ, gain control
	Microphon chanal: 1 x mono via jack, channel control via rotary dial, cue mix function
	Master output: 1 x stereo via RCA, channel control via rotary dial
	Headphones output: 1 x stereo via jack, channel control via rotary dial
Max. level:	Output: master +19 dBu
Housing design:	Desktop console housing
Dimensions:	Width: 19 cm
	Depth: 26 cm
	Height: 13,7 cm