

## OMNITRONIC PM-202F 2-Channel DJ Mixer with Filter and Bluetooth

DJ mixer with Bluetooth connectivity and sound filter

Art. No.: 10006863 GTIN: 4026397731071

**List price: 189.21 €** 

incl. 19% VAT.

## Features:

- Bluetooth signal routable to channel 1 and 2
- DJ microphone channel with level control and 2-band equalizer
- Crossfader with adjustable curve and reverse function
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Master channel with level control and stereo LED level meter
- 4 line and 2 phono inputs via RCA jacks
- Additional recording output
- DJ filter LPF/HPF bipolar per channal
- Control via Bluetooth
- Bluetooth: operating range up to 15m
- Desktop console housing
- For application areas such as: Party room; mobile use; mobile djs / entertainer

## **Technical specifications:**

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	Max. 8 W
Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz

## Logistic

EAN / GTIN: 4026397731071

Weight: 2,50 kg Length: 0.31 m Width: 0.30 m Heigth: 0.13 m

S/N ratio:	>80 dB
THD:	<0,1 % at 1 kHz
DJ filter:	Per channal: LPF/HPF bipolar,
Control:	Bluetooth
Bluetooth device name:	PM-202F
Range:	Bluetooth: range up to 15m
Crosstalk:	>60 dB
Control elements:	Crossfader, Crossfade curve control, crossfade reverse switch, FX Parameter control, power switch
Status LED:	Power, master level meter
Connections:	Input: line/phono via 2 x stereo RCA Input: line via 2 x stereo RCA Input: microphone via 1 x 3-pin XLR (F) mounting
	version Input: antenna via 1 x SMA (F) mounting version Input: Earthing connection via 2 x screw terminal Output: master via 2 x 3-pin XLR (M) mounting version
	Output: master via 1 x stereo RCA
	Output: rec. via 1 x stereo RCA
	Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
	Output: headphones via 1 x 3.5 mm jack (stereo) mounting version
Channels:	Input chanel: 2 x stereo with Line-Line/Phono-Bluetooth switch via RCA, channel control via 60mm fader, 2-band tone control EQ, gain control, CUE switch
	Microphon chanal: 1 x mono via XLR, channel control via rotary dial, 2-band tone control EQ
	Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol
	Headphones output: stereo via jack, channel control via rotary dial, cue mix function
	Rec. output: stereo via RCA
Material:	Metal
Color:	Black
Housing design:	Desktop console housing
Dimensions:	Length: 30,5 cm Width: 19,0 cm Height: 11,0 cm
Weight:	2,20 kg
Power cord	
Cable length:	2,10 m detachable