

OMNITRONIC PM-211 DJ mixer

2-channel DJ mixer

Art. No.: 10006870

GTIN: 4026397467130



The article is no longer in our assortment.

Features:

- 2 input channels with gain control and phono/line switching
- DJ microphone input with talkover selector, level and tone control
- Adjustable front aux input for portable music players (e.g. iPod)
- Pre-fader listening (CUE) to the input channels via adjustable headphones output, with cue mix control
- Crossfader for crossfading between both channels
- 5-digit stereo LED level meter, switchable between master and PFL signal
- Additional recording output
- Operation via supplied power unit

Logistic

EAN / GTIN: 4026397467130

Weight: 1,40 kg

Length: 0.30 m

Width: 0.20 m

Height: 0.10 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
---------------	-----------------

Power consumption:	3,00 W
--------------------	--------

Frequency range:	20 - 20000 Hz
------------------	---------------

Dimensions:	Width: 18 cm
	Depth: 14 cm
	Height: 6,5 cm

Weight:	1,15 kg
---------	---------

	via supplied power unit
--	-------------------------

Inputs:

Line/phono:	2 x stereo RCA
Aux:	3.5 mm stereo jack
DJ microphone:	6.3 mm jack, unbal.
Outputs:	
Master:	stereo RCA
Record:	stereo RCA
Headphones output:	6.3 mm stereo jack (min. 32 ohms)
S/N ratio:	>75 dB
Distortion:	<0.07 %
Dimensions (L x W x H):	180 x 140 x 65 mm