

OMNITRONIC PM-322P 3-channel DJ Mixer with Bluetooth & USB Player

Art. No.: 10006874

3-channel DJ mixer with Bluetooth and MP3 player

GTIN: 4026397653403



Features:

- 3 input channels with gain control, 3-band equalizer, cue button and channel fader
- DJ microphone channel with level control and 2-band equalizer
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Crossfader with adjustable curve and reverse function
- Master channel with level control and 6-digit stereo LED level meter, switchable between master and PFL signal
- 6-digit stereo LED level meter
- 6 line and 2 phono inputs via RCA jacks
- Balanced XLR and RCA outputs
- Record output, independent of the master
- Control via Bluetooth
- Operating range up to 10m with line-of-sight
- LCD display
- Desktop console housing
- For application areas such as: Party room; mobile djs / entertainer; mobile use

Logistic

EAN / GTIN: 4026397653403

Weight: 3,17 kg

Length: 0.31 m

Width: 0.31 m

Height: 0.14 m

Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption: 25 W

Protection class: Protection class II

Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Control:	Bluetooth
Bluetooth:	Version: 4.2 + EDR Profiles: A2DP, AVRCP
Bluetooth device name:	PM-322P
Audio player:	USB + Bluetooth
Range:	Range up to 10m with line-of-sight
Carrier frequency:	2.4 GHz
Housing color:	Black
Display type:	LCD display
Control elements:	Audio player, crossfader, cue mix function, source selector, crossfade curve switch; crossfade reverse switch
Status LED:	Switchable master level meter, clip, CUE, power
Connections:	Input: line via 4 x stereo RCA Input: line/phono via 2 x stereo RCA Input: audio player via 1 x USB A (F) mounting version Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version Output: master via 2 x 3-pin XLR Output: master via 2 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input channel: 1 x stereo with line-line-player switch via RCA or player, channel control via fader, 3-band tone control EQ, gain control, CUE switch Input channel: 2 x stereo with line-line/phono switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch Microphone channel: 1 x mono via jack, channel control via rotary dial, 2-band tone control EQ, cue mix function Master output: 1 x stereo via XLR or RCA, channel control via rotary dial Headphones output: 1 x stereo via jack, channel control via rotary dial
Music format:	MP3, WAV; WMA
USB port:	Type A
Housing design:	Desktop console housing
Dimensions:	Length: 28.3 cm Width: 23 cm Height: 10.7 cm
Weight:	2.58 kg
Available storage media:	USB devices max. 32GB (FAT 32)

Scope of delivery:

1 x mixer
1 x user manual
1 x power cord
1 x RCA cable

1 x declaration of conformity