

OMNITRONIC PM-422P 4-Channel DJ Mixer with Bluetooth & USB Player

Art. No.: 10006878

4-channel DJ mixer with Bluetooth and MP3 player

GTIN: 4026397653410

**List price: 272.51 €**

incl. 19% VAT.

Features:

- 4 input channels with gain control, LED level meter, 3-band equalizer, cue button and channel fader
- DJ microphone channel with level control, 2-band equalizer, on/off and talkover switch
- Integrated Bluetooth audio streaming for your smartphones and tablets
- MP3 player with USB port and blue LCD screen
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Crossfader with assignment switches and adjustable curve
- Master channel with level and balance control
- 10-digit stereo LED level meter
- Adjustable monitor output (DJ booth)
- 10 line and 2 phono inputs via RCA jacks
- Balanced XLR and RCA outputs
- Record output, independent of the master
- Controlling by Bluetooth
- Use a operating range up to 10m
- Desktop console housing

Logistic

EAN / GTIN: 4026397653410

Weight: 4,17 kg

Length: 0.37 m

Width: 0.29 m

Height: 0.13 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	25 W
Protection class:	Class II

Power connection:	Mains input C8 "figure 8" mounting version Power supply cord with Euro plug (provided)
Control:	Bluetooth
Bluetooth:	Version: 4,2 + EDR Profiles: A2DP, AVRCP
Audio player:	USB + Bluetooth
Display type:	Monochrome LCD display
Control elements:	Audio player, Talk over, Crossfader selector switch, Crossfader, Crossfade curve switch
Status LED:	Chanal level meter, master level meter, CUE, ON AIR, power
Connections:	Input: 6 x line via stereo RCA Input: 2 x line/phono via stereo RCA Input: 1 x Microphone via 6.3 mm jack socket (mono) mounting version Input: 1 x Audio player via USB A (F) mounting version Output: 1 x master via stereo RCA Output: 2 x master via 3-pin XLR Output: 1 x rec. via stereo RCA Output: 1 x booth via stereo RCA Output: 1 x headphones via 6.3 mm jack socket (stereo) mounting version
Chanals:	Input channel: 1 x stereo with Line-line-player switch via RCA or player, channel control via fader, 3-band tone control EQ, gain control, CUE switch, Input channel: 1 x stereo with Line-line switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch, Input channel: 2 x stereo with Line-Line/Phono switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch, Microphon chanal: 1 x mono via Plug 6,3mm/3,5mm (Jack), channel control via Rotary dial, 2-band tone control EQ, Talk over switch, ON AIR switch, Master output: 1 x stereo via XLR or RCA, channel control via Rotary dial, balancecontrol, Booth output: 1 x stereo via RCA, channel control via Rotary dial, Cue-mix-function, Headphones output: 1 x stereo via Plug 6,3mm/3,5mm (Jack), channel control via Rotary dial
Format:	MP3, WAV; WAV
Carrier frequency:	2,4 GHz
USB port:	Typ A
Range:	10 m
Housing design:	Desktop console housing
Dimensions:	Length: 35 cm Width: 26,6 cm Height: 10,5 cm
Weight:	3,46 kg
Audio player	
Available storage media:	USB devices max. 32GB (FAT 32)