

OMNITRONIC EM-260 Entertainment Mixer

6-channel microphone/line mixer

Art. No.: 10007075

GTIN: 4026397179118



List price: 224.91 €

incl. 19% VAT.

Description:

OMNITRONIC Entertainment Mixer Series

The modern entertainment industry, especially hotels, bars or theme parks, requires very high standards in quality and features for sound devices.

The OMNITRONIC EM-series is especially designed for this industry and offers the highest flexibility and quality in very small mixer casings.

The EM-series offers a variety of connection possibilities and also convinces by an ergonomic design and easy use.

The special housing design and the state-of-the-art construction are further reasons which make the EM-series the first choice for installers.

Features:

- 6 inputs (3 x mic/line and 3 x line) for mixing to 1 stereo output
- Ideal e.g. for karaoke when microphones need to be mixed with CDs
- 3 mono input channels mic/line (XLR, bal.), switchable
- 3 stereo line input channels (RCA)
- Clip LED for each microphone channel
- Each microphone input with optional 12 V phantom power
- FX send/return with FX level control
- Stereo master out (6.3 mm jack) with 2-band equalizer (highs and lows) and level control
- Stereo record output (RCA)
- Rack installation, 1 U
- (19") 48.3 cm rack installation 1 U

Logistic

EAN / GTIN: 4026397179118

Weight: 2,60 kg

Length: 0.53 m

Width: 0.27 m

Height: 0.09 m

Technical specifications:

Power supply:	115/230 V AC, 50/60 Hz
Power consumption:	35 W
Protection class:	Class I
Power connection:	Mains input IEC connector (M) mounting version Power supply cord with safety plug (provided)
Frequency range:	20 - 20000 Hz
Phantom power:	12 V DC
Housing color:	Silver
Control elements:	Phantom power switch, power switch, FX send/return control
Status LED:	Power, clip
Connections:	Input: 3 x mic/line via 3-pin XLR Input: 3 x line via stereo RCA Input: 2 x FX via 6.3 mm jack socket (mono) mounting version Output: 1 x rec. via stereo RCA Output: 2 x master via 6.3 mm jack socket (mono) mounting version Output: 1 x FX via 6.3 mm jack socket (stereo) mounting version
Chanals:	Input channel: 3 x stereo via RCA, channel control via Rotary dial, 2-band tone control EQ 100Hz/10kHz Microphon channel: 3 x mono with Mic-line switch via XLR, channel control via Rotary dial Master output: 1 x stereo via Plug 6,3mm/3,5mm (Jack), channel control via Rotary dial
Max. level:	Input: Microphone +14 dB Input: line +24 dB
Material:	Metal
Color:	Silver
Housing design:	(19") 48.3 cm rack installation 1 U
Dimensions:	Width: 48,3 cm Depth: 12,3 cm Height: 4,45 cm
Weight:	2,20 kg