

## OMNITRONIC EP-220NET Preamplifier with Internet Radio, DAB+ and Bluetooth

19" preamplifier mit Internetradio, DAB+, Bluetooth and IR remote control

No.: 10007079

GTIN: 4026397695359



**List price: 355.81 €**

incl. 19% VAT.

### Features:

- Internet radio with DAB+ and FM tuner, Bluetooth and UPnP/DLNA support
  - Wide range of streaming options via Wi-Fi, LAN jack and Bluetooth
  - Large 2" TFT color display, easy jog dial operation, equalizer presets, sleep timer and alarm function
  - Access to thousands of radio stations worldwide
  - Station scan by genre, station name, location
  - 4 stereo line inputs (RCA) on the back panel
  - 3.5 mm AUX input on the front panel
  - 1 combo microphone input with controls for volume, bass and treble on the front panel
  - Audio source selector
  - Controls for volume, bass and treble
  - 3 stereo master outputs
  - Digital and analog audio outputs (Toslink, coaxial, RCA)
  - Control via Wi-Fi; IR remote control
  - 2.4 GHz license-free worldwide
  - Desktop console housing
  - (19") 48.3 cm rack installation possible
  - For application areas such as: Installation; restaurants, bars and hotels
- Package contents**
- 1 x device, 1 x power cord, 1 x remote control, 2 x antenna, 1 x RCA cable, 4 x foot, 1 x user manual, 1 x declaration of conformity

### Logistic

EAN / GTIN: 4026397695359

Weight: 2,70 kg

Length: 0.55 m

Width: 0.27 m

Height: 0.07 m

## Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	6 W
IP classification:	IP20
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Frequency range:	20 - 20,000 Hz
S/N ratio:	>100 dB
THD:	<0,1 % at 1 kHz
Wi-Fi:	Standard: IEEE 802.11 b/g/n Security protocol: WEP/WPA/WPA2
Network connection:	Protocol: Ethernet TCP/IP via RJ-45 (F) mounting version, 10/100 Mbit/s
Impedance:	Input: 10 kOhm , unbal. Input: 20 kOhm , bal.
Control:	Wi-Fi; IR remote control
Bluetooth:	Version: 4,2 + EDR
Bluetooth device name:	EP-220NET
Audio player:	FM-tuner + Internet radio + BT + DAB+
Frequency band:	2.4 GHz
Housing color:	Black
Display type:	Multicolor TFT display
Tuner frequency range:	FM 87-108 MHz, DAB(+) 174,928-239,200 MHz
Control elements:	Power switch, source selector, level control, tone control, menu; navigation keys, encoder
Status LED:	Power
Connections:	Antenna via 1 x SMA (F) mounting version Network connection via 1 x RJ-45 (F) mounting version Input: antenna via 1 x Belling-Lee (F) mounting version Input: line via 4 x stereo RCA Input: AUX via 1 x 3.5 mm jack (stereo) mounting version Input: microphone via 1 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version) Output: line via 2 x 3-pin XLR (M) mounting version Output: line via 2 x 6.3-mm-jack (bal.) Output: line via 1 x stereo RCA Output: optical via 1 x toslink Output: coaxial (S/PDIF) via 1 x RCA (F) mounting version
Channels:	Microphon chanal: 1 x mono via Combination socket (XLR/jack), channel control via rotary dial, 2-band tone control EQ  Master output: stereo, channel control via rotary dial, 2-band tone control EQ, source selector
Music format:	MP3, AAC/AAC+; FLAC

Max. level:	Input: line +20 dBu Output: +22 dBu
Material:	Metal
Housing design:	Desktop console housing (19") 48.3 cm rack installation possible
Dimensions:	Width: 48,3 cm Depth: 19 cm Height: 4,4 cm
Weight:	2,20 kg
Remote control	
Power supply:	3V
Battery:	2 x Micro (AAA) (not included)