

OMNITRONIC HRS-802 Home recording mixer

Compact 8-channel home-recording mixer

Art. No.: 10040203

GTIN: 4026397262759



The article is no longer in our assortment.

Features:

- Low noise 8-channel Mic/Line-mixer
- 4 mono inputs with XLR sockets
- 2 stereo inputs with balanced 6.3 mm jack sockets
- Stereo inputs can also be operated mono
- 2-band EQ for all mono inputs
- Aux-Send per channel for controlling external effectors
- Separate Main Mix and headphones outputs
- Tape inputs assignable to Master or headphones

Logistic

EAN / GTIN: 4026397262759

Weight: 2,10 kg

Length: 0.28 m

Width: 0.28 m

Height: 0.10 m

Technical specifications:

| | |
|--------------------|--|
| Power consumption: | 20,00 W |
| Dimensions: | Width: 22,3 cm Depth: 18,2 cm Height: 4,3 cm |
| Weight: | 1,60 kg |
| Power supply: | 2 x 15 V AC, 50 Hz via included power unit |
| Inputs: | |
| 4 mono | XLR |
| 2 stereo | balanced 6.3 mm jacks |

| | |
|-------------------------|-------------------------|
| 1 Tape In | RCA |
| Outputs: | |
| 1 Master-Out | balanced 6.3 mm jacks |
| 1 Aux Send: | balanced 6.3 mm jacks |
| 1 Tape Out | RCA |
| 1 Phones | balanced 6.3 mm jacks |
| 1 Rec | RCA |
| Frequency range: | |
| Microphone: | 10-60000 Hz, ± 3 dB |
| Mono: | 10-60000 Hz, ± 3 dB |
| Stereo: | 10-55000 Hz, ± 3 dB |
| Distortion: | 0.01 % |
| S/N-ratio: | 112 dB |
| Tone control/channel: | |
| Treble: | ± 15 dB at 12 kHz |
| Bass: | ± 15 dB at 80 Hz |
| Dimensions (W x D x H): | 223 x 182 x 43 mm |