

OMNITRONIC RM-1422FXA USB Rack Power Mixer

19" powered mixer, 2 x 400 W, with 12 channels, DSP FX unit and MP3 player

Art. No.: 10040302

GTIN: 4026397683233



List price: 403.41 €

incl. 19% VAT.

Features:

- Audio mixer and digital amplifier in a 19" housing
- Built-in USB audio interface allows recordings and playback of digital audio files with a computer (PC and Mac)
- 24 bit DSP FX unit with 16 different effects, e.g. reverb, echo and flanger
- 6 mono input channels with gain control, 2-way EQ, pan control and channel fader
- 2 stereo input channels with 2-way EQ, balance control and channel fader
- 8 channel inserts
- Tape input and output
- Separate main mix and control room outputs
- 2 aux send outputs
- Adjustable headphones output
- +48 V phantom power, can be switched centrally
- 4-digit stereo LED level display
- MP3 player with Bluetooth, SD card slot, USB input, LCD and IR remote control
- Digital signal processor
- Controlling by IR remote control; Bluetooth
- (19") 48.3 cm rack installation 3 U

Logistic

EAN / GTIN: 4026397683233

Weight: 7,65 kg

Length: 0.40 m

Width: 0.53 m

Height: 0.21 m

Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 115 W 1/8 power

Protection class: Class I

Output power:	2 x 250 W RMS (8 ohms) 2 x 400 W RMS (4 ohms)
Power connection:	Power supply cord with safety plug (provided)
Battery:	1 x Button cell 3.0 V CR2025 lithium manganese built-in
Frequency range:	20 - 20000 Hz
S/N ratio:	>89 dB
THD:	<0,05 % at 1 kHz
DSP:	Digital signal processor
Control:	IR remote control; Bluetooth
Audio player:	USB + SD + Bluetooth
Equalizer:	Chanal: 2 x 2-band tone control stereo Chanal: 8 x 2-band tone control mono
Connections:	Input: 8 x Microphone via 3-pin XLR Input: 12 x line via 6.3 mm jack socket (stereo) mounting version Input: 1 x line via stereo RCA Input: 2 x AUX via 6.3 mm jack socket (stereo) mounting version Output: 2 x AUX via 6.3 mm jack socket (stereo) mounting version Output: 1 x rec. via stereo RCA Output: 2 x master via 3-pin XLR Output: 2 x speakers via speaker built-in socket (F)
Input channels:	2 x stereo via Plug 6,3mm/3,5mm (Jack) 8 x mono via XLR or jack
USB port:	Typ A
Housing design:	(19") 48.3 cm rack installation 3 U
Dimensions:	Width: 48,3 cm Depth: 34 cm Height: 13,35 cm
Weight:	6,60 kg