

OMNITRONIC RM-1422FXA USB Rack Power Mixer

19" powered mixer, 2 x 400 W, with 12 channels, DSP FX unit and MP3 player

Art. No.: 10040302

GTIN: 4026397683233



Features:

- Audio mixer and digital amplifier in a 19" housing
- Built-in USB audio interface allows recordings and playback of digital audio files with a computer (PC and Mac)
- 6 mono input channels with gain control, 2-way EQ, pan control and channel fader
- 2 stereo input channels with 2-way EQ, balance control and channel fader
- 8 channel inserts
- Tape input and output
- Separate main mix and control room outputs
- 2 AUX send outputs
- Adjustable headphones output
- +48 V phantom power, can be switched centrally
- 4-digit stereo LED level display
- (19") 48.3 cm rack installation 3 U
- Digital signal processor 24 bit with 16 effects
- Control via IR remote control; Bluetooth
- For application areas such as: Clubs/dancing school; stage; theater; concerts/FoH's; rental

Logistic

EAN / GTIN: 4026397683233

Weight: 8,05 kg

Length: 0.53 m

Width: 0.42 m

Height: 0.23 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	115 W 1/8 power
Protection class:	Protection class I
Output power:	2 x 250 W RMS (8 ohms)

	2 x 400 W RMS (4 ohms)
Power connection:	Power supply cord with safety plug (provided)
Battery:	1 x button cell 3.0 V CR2025 lithium manganese built-in
Frequency range:	20 - 20000 Hz
S/N ratio:	>89 dB
THD:	<0.05 % at 1 kHz
DSP:	Digital signal processor 24 bit with 16 effects
Phantom power:	48 V DC
Control:	IR remote control; Bluetooth
Bluetooth device name:	Bluetooth
Audio player:	USB + SD + Bluetooth
Control elements:	Level control per channel, Master control, tone control, phantom power switch
Connections:	Input: microphone via 8 x 3-pin XLR Input: line via 12 x 6.3 mm jack socket (stereo) mounting version Input: line via 1 x stereo RCA Input: AUX via 2 x 6.3 mm jack socket (stereo) mounting version Output: AUX via 2 x 6.3 mm jack socket (stereo) mounting version Output: rec. via 1 x stereo RCA Output: master via 2 x 3-pin XLR Output: speaker via 2 x speaker built-in socket (F)
Channels:	Input channel: 2 x stereo via jack, 2-band tone control EQ, gain control, panorama control
Input channels:	8 x mono via XLR or jack
Equalizer:	Channel: 8 x 2-band tone control mono
Available storage media:	USB devices/SD cards
USB port:	Type A
Color:	Black
Housing design:	(19") 48.3 cm rack installation 3 U
Dimensions:	Width: 48.3 cm Depth: 34 cm Height: 13.35 cm
Weight:	6.55 kg

Scope of delivery:

- 1 x remote control
- 1 x battery
- 1 x user manual
- 1 x power cord
- 1 x mixer
- 1 x declaration of conformity