

## **OMNITRONIC PNM-6 Nearfield Monitor**

Active speaker with 6,5" woofer, 2,5" driver, 40 W RMS

Art. No.: 11036456 GTIN: 4026397513929



# The article is no longer in our assortment.

### Features:

- Active nearfield monitor for DJs and producers
- 2-way bass-reflex system with biamp amplifier
- Separate controls for volume, high and low frequencies
- For home studio and multimedia use
- 6.3 mm jack and 3-pin XLR input for connection the audio source
- 17 cm bass-midrange speaker and 2.5 cm dome tweeter with wave guide
- Rugged black MDF cabinet

#### **Technical specifications:**

Power supply:	115/230 V AC, 50/60 Hz
Power consumption:	100,00 W
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with Euro plug (provided)
Power:	Program: 80W
	Rated: 40W RMS
Frequency range:	45 - 20000 Hz
Sensitivity:	88 dB
Connections:	Line via 1 x 6.3 mm plug (unbal.)
	Line via 1 x 3-pin XLR

#### Logistic

EAN / GTIN: 4026397513929

Weight: 8,10 kg Length: 0.31 m Width: 0.29 m Heigth: 0.43 m

Speaker:	1 x woofer 6,5"	
	1 x dome tweeter 2,5"	
Type of speaker:	Monitor for studios	
Dimensions:	Width: 23 cm	
	Depth: 21 cm	
	Height: 34 cm	
Weight:	7,35 kg	