

INTUSONIC DLA26 Zone Distributor 2-IN-6

Stereo 2-in-6 splitter for setting up large multi-zone applications

Art. No.: 12604177

GTIN: 5060502923233



Description:

The INTUWORX DLA26 is a stereo 2-in-6 splitter allowing to build large multi-zone systems fed with different levels of the same two selectable input signals. Every output/zone features a 2-band EQ, volume control and overload LED on the front panel, and can be switched to mono on the rear panel if required. Likewise, a 100Hz HPF can be engaged per zone on the rear panel, to cater for connected speaker systems potentially unable to reproduce very low frequencies. Limiting the range of the front panel volume controls, additional rear-panel controls allow to set the maximum volume for every output/zone. Aside from its splitter/zoner functions, the DLA26 also adds versatility by allowing to feed a signal from a mobile device via its front-panel 3.5mm input, and by its additional emergency features which include a mute contact and an auto-sensing emergency priority input. The DLA26 is the perfect companion to single-output mixers to build multi-zone systems.

Features:

- Desktop console housing
- For further information about this product, please refer to the Data Sheet under "Downloads"

Technical specifications:

Power supply:	115/230 V AC, 50/60 Hz
Power consumption:	Max. 12 W
Power connection:	Mains input via IEC (M) power supply cord with safety plug (provided)
S/N ratio:	>82 dB

Logistic

EAN / GTIN: 5060502923233

Weight: 3,60 kg

Length: 0.54 m

Width: 0.33 m

Height: 0.10 m

THD:	<0.06 % at 1 kHz
Crosstalk:	>72 dB
Max. level:	Input: +17.8 dBu
Color:	Black
Housing design:	Desktop console housing
Dimensions:	Width: 48.3 cm Depth: 22 cm Height: 4.4 cm
Weight:	3.05 kg

Scope of delivery:

- 1 x user manual
- 1 x device
- 1 x power cord
- 7 x screw plug-in terminal
- 1 x plug (male)
- 4 x foot