

OMNITRONIC AB-1000 Antenna booster

Antenna booster

Art. No.: 13063030 GTIN: 4026397195354



The article is no longer in our assortment.

Features:

- Antenna booster for receiver DR-1000 (two antenna boosters are needed for operation)
- Improves the interference safety and enlarges the range
- Power supply via receiver DR-1000 or antenna distributor UA-1000
- Bracket for wall installation
- 1.5 cm (5/8") thread for stands
- Rugged steel housing
- BNC antenna cable must be ordered separately

Technical specifications:

Frequency range:	470 - 870 Hz
Dimensions:	Width: 7,6 cm
	Depth: 1,8 cm
	Height: 5,1 cm
Power supply:	12-18 V DC
	via DR-1000 or UA-1000
Antenna gain:	1.8 dBi
Booster gain:	10 dB
Coverage angle:	360°
Antenna connector:	BNC

Logistic

EAN / GTIN: 4026397195354 Weight: 0,38 kg Length: 0.38 m Width: 0.10 m Heigth: 0.07 m

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

Receiver output:	BNC
Dimensions:	76 x 18 x 76 mm
Weight:	140 g