

OMNITRONIC AD-500 Antenna Distributor Set

Antenna distributor

Art. No.: 13063032

GTIN: 4026397438321



The article is no longer in our assortment.

Features:

- Active antenna distributor for operating up to four UHF receivers on one pair of multi-antennas
- Improves the interference safety and enlarges the range
- Replaces the respective antennas and PSUs of the individual receivers
- Up to five antenna distributors AD-500 can be connected among each other for use of 16 microphones in total
- Directional antennas made of durable glass/copper with 1.5 cm thread (5/8") for stands
- Low-voltage outputs for supplying four UHF receivers, incl. matching connection cables
- Use in the entire UHF frequency range (600 - 900 MHz)
- All antenna connections via BNC jacks
- Rack installation with 1 unit
- Rugged steel housing
- Incl. padded transport case, with aluminum profile frames

Logistic

EAN / GTIN: 4026397438321

Weight: 5,80 kg

Length: 0.55 m

Width: 0.40 m

Height: 0.14 m

Technical specifications:

Type:	Antennas and distributors
Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	40,00 W
Dimensions:	Width: 48,3 cm Depth: 21 cm Height: 4,45 cm
Weight:	5,77 kg

Frequency range:	600-900 MHz
Impedance:	50 ohms
Antenna connectors:	2 x BNC
Receiver outputs:	8 x BNC
Low-voltage outputs:	4 x 12 V DC
Dimensions distributor:	482 x 210 x 44 mm
	Rack installation with 1 U
Dimensions antennas:	315 x 336 mm