

## OMNITRONIC UHF E-FLEX Bodypack 823-832/863-865 MHz

Bodypack transmitter with PLL multifrequency transmitter

Art. No.: 13063374

GTIN: 4026397740264

**The article is no longer in our assortment.**

### Features:

- Quick pairing at the touch of a button
- Receiver automatically adopts frequency setting
- 16 channels selectable
- Sensitivity adjustable
- 4 digit 7-segment LED display
- Charge status indicator
- Operating range up to 30m with line-of-sight
- UHF 823 - 832 MHz License-free and approved in large parts of Europe
- UHF 863 - 865 MHz License-free and approved in Europe

#### Package contents

- 1 x microphone, 1 x user manual, 1 x declaration of conformity

### Logistic

EAN / GTIN: 4026397740264

### Technical specifications:

Type:	Pocket transmitter
Power supply:	3V DC
Power connection:	Battery/battery pack
Battery:	2 x Mignon (AA) (not included)
Frequency range:	50 - 15000 Hz
Range:	Range up to 30m with line-of-sight
Frequency band:	UHF 823 - 832 MHz; UHF 863 - 865 MHz

RF power output:	10 mW
Modulation:	FM
Frequency selection:	16 switchable frequencies In 2 groups
Connector type:	Mini XLR (M) 3-pin mounting version
Display type:	4 digit 7-segment LED display
Display:	Charge status indicator , channel , frequency , Mute
Control elements:	Sensitivity rotary dial, frequency selector switch
Status LED:	Power
Switch:	On/off/mute switch
Material:	Plastic
Color:	Black
Dimensions:	Width: 6,9 cm Depth: 2,5 cm Height: 9,4 cm
Weight:	0,069 kg