

## **OMNITRONIC WS-1R 2.4GHz Receiver**

Digital audio transmission system 2.4 GHz









0.0

# The article is no longer in our assortment.

#### Features:

- Digital receiver for wireless reception of stereo audio signals with 2.4 GHz
- Transmit music via radio from your PC or MP3 player to your stereo or active speaker with outstanding audio quality
- Simultaneous operation of an unlimited number of receivers possible
- Digital transmission in the 2.4 GHz range provides for high resistance to interference and unique sound quality (16 bits/48 kHz)
- Operating range up to 30 m indoors and up to 50 m outdoors
- Stereo audio output: RCA L/R
- Push button for pairing with the transmitter
- Removable rod antenna
- Operation via supplied power unit
- Rugged, compact metal housing
- Supports PC and Mac
- 2.4 GHz ISM band license-free worldwide
- Control via Wi-Fi
- Operating range up to 50m in the open air
- Operating range up to 30m in buildings
- 2.4 GHz license-free worldwide

### Logistic

EAN / GTIN: 4026397512052 Weight: 0,28 kg Length: 0.23 m Width: 0.16 m Heigth: 0.04 m

## Technical specifications:

Туре:	Audio transmission
Power connection:	Mains input via USB, type B power supply cord with AC adapter (provided)

Frequency range:	20 - 20000 Hz
S/N ratio:	>96 dB
Control:	Wi-Fi
Range:	Range up to 50m in the open air Range up to 30m in buildings
Frequency band:	2.4 GHz
Material:	Metal
Dimensions:	Width: 11 cm Depth: 6,5 cm Height: 6,3 cm
Weight:	0,22 kg
Power supply:	5 V DC, 500 mA
	via USB port or supplied PSU
Carrier frequency:	2406-2472 MHz (ISM), 32 channels
Modulation:	GFSK
THD:	-70 dB
Crosstalk:	-96 dB
USB port:	2.0, type mini B
Line output:	RCA L/R
Converter:	16 bits
Sample rate:	48 kHz