eurolite®

EUROLITE Set 2x Flexilight gooseneck XLR + front panel







The article is no longer in our assortment.

Features:	
-----------	--

EUROLITE Flexilight Gooseneck Lamp XLR SM-3a

Gooseneck lamp, rectangular reflector

- Gooseneck lamp with rectangular reflector
- 12V/5W lamp
- 3-pin XLR plug
- Illuminates turntables, mixers etc.

EUROLITE Flexilight Racklight XLR Front Panel

19" front panel for connection of 2 gooseneck lamps with XLR

- For 2 gooseneck lamps (12V/5W or LED) with XLR plug
- Two clamps for fixation of the goosenecks
- Control via on/off switch on device; rotary dial for brightness
- (19") 48.3 cm rack installation

Technical specifications:

Weight:

1,11 kg

Logistic

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

EUROLITE Flexilight Gooseneck Lamp XLR SM-3a

Power supply:	12V AC 500 mA
Power consumption:	5 W
Power connection:	Mains input via 3-pin XLR (M) connector
Dimensions:	Length: 38,5 cm
Weight:	0,13 kg
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting

EUROLITE Flexilight Racklight XLR Front Panel

Power supply:	230 V AC, 50 Hz
	12V DC 1000 mA
Power consumption:	10 W
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Control:	On/off switch on device; rotary dial for brightness
Housing design:	(19") 48.3 cm rack installation
Dimensions:	Width: 48,3 cm
	Depth: 4 cm
	Height: 4,45 cm
Weight:	0,85 kg