


EUROLITE Set LED KLS-180 + QuickDMX Wireless Receiver

Bar with 4 RGBW spots and 4 white strobe LEDs including wireless DMX receiver

Art. No.: 2000339

GTIN:



Features:

- Crossbar with integrated DMX control unit and stand sleeve
 - Compact lightweight
 - Color blend stepless; color change adjustable; colors preset; Dimmer electronic
 - Strobe effect
 - The device is cooled by passive convection cooling
 - Control via stand-alone; DMX; IR remote control; sound to light via microphone; master/slave function; QuickDMX via 5-pin XLR (M) mounting version (optional)
 - Flicker-free
 - With a beam angle of 9°
 - With mounting bracket
 - Monochrome 4 digit 7-segment LED display
 - Mains input and output for power linking up to 8 units
 - For application areas such as: Clubs/dancing school; decoration; mobile djs / entertainer; party room; restaurants, bars and hotels
 - Silent operation
 - Application possibility: On stand
- spotlight**
- 4 LEDs 8 W SMD 9080 4in1 RGBW (homogenous color mix)
4 spots controlled separately
- bar**
- 4 LEDs 1 W SMD 8072 cold white (CW)
 LEDs controlled separately
 - <p>EUROLITE QuickDMX Wireless receiver phantom-power
 - <h2 class="featureSatz">Compact wireless DMX receiver 2.4 GHz, phantom powered</h2>User-friendly 5-pin XLR adapter(female) with swivel antenna
 - Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations

Logistic

- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- Can receive and process up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Technical specifications:

Weight: 4.94 kg

EUROLITE LED KLS-180 Compact Light Set

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	80 W
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Power output:	1 x IEC connector (F) mounting version
Fuse:	5 x 20 mm, T 1 A fuse replaceable
Lamp type:	LED lamp
Flash rate:	0.5 - 20 Hz
DMX channels:	3; 4; 8; 21
DMX input:	3-pin XLR (M) mounting version
DMX output:	3-pin XLR (F) mounting version
Cooling:	Passive convection cooling
Control:	Stand-alone; DMX; IR remote control; sound to light via microphone; master/slave function; QuickDMX via 5-pin XLR (M) mounting version (optional)
Fixtures available for:	LED PC-Control 512; Light Captain; Light J; EASY SHOW 1; EASY SHOW 2; EASY SHOW 3; Colorchief
Projection:	Flicker-free
PWM frequency:	9000 Hz
Beam angle (1/2 peak):	9°
Beam angle (1/10 peak):	18°
Housing color:	Black
Attachment system:	Ø 35mm 1x mounting bracket
Display type:	Monochrome 4 digit 7-segment LED display
Material:	Metal; plastic
Dimensions:	Width: 60.5 cm Depth: 14 cm Height: 23 cm

Weight:	4.85 kg
Noise classification:	Class 0 (no noise at all)
Photobiological safety:	Risk Group 0
LED type:	4 x 8 W SMD 9080 4in1 RGBW (homogenous color mix)
LED type:	4 x 1 W SMD 8072 cold white (CW)
Diameter mounting holes:	3 x Ø11mm; 2 x Ø3mm
Material:	Metal, 2 mm
Cable construction:	3 x 0.75 mm ² H05VV-F
Battery:	1 x button cell 3.0 V CR2025 lithium manganese built-in
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting

EUROLITE QuickDMX Wireless receiver phantom-power

Power supply:	5V DC
Power connection:	Mains input via 5-pin XLR (W) connector
DMX channels:	Input 512
DMX output:	1 x 5-pin XLR (F)
Control:	DMX; QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21.2 cm Diameter: Ø 1.8 cm
Weight:	0.10 kg

Scope of delivery:

1 x EUROLITE LED KLS-180 Compact Light Set

1 x spotlight
1 x power cord
1 x bag
1 x remote control
1 x battery
1 x user manual

1 x EUROLITE QuickDMX Wireless receiver phantom-power

1 x device
1 x user manual
1 x declaration of conformity