



**List price: 355.81 €**

incl. 19% VAT.

### Features:

#### EUROLITE LED B-40 HCL Beam Effect MK2

LED beam effect with RGBWA+UV color mixing, incl. remote-control

- 5 powerful LEDs 10 W 6in1 HCL RGBWA/UV<BR> segments controlled separately
- 8 integrated show programs
- Control via IR remote control; stand-alone; Sound to light via Microphone; DMX; QuickDMX via USB (optional); W-DMX by wireless solution via USB (optional); CRMX by LumenRadio via USB (optional); Master/slave function
- Multi beam effect; Strobe effect
- With Omega bracket
- Monochrome 4 digit 7-segment LED display
- Rotation speed adjustable; Dimmer electronic; color blend stepless
- Preprogrammed in Light J; Light Captain; EASY SHOW 2; EASY SHOW 3
- For application areas such as: Clubs/dancing school; Wedding/gala/events; mobile djs / entertainer; restaurants, bars and hotels
- Application possibility: Standing; suspended

#### Package contents

- 1 x light effect, 1 x user manual, 1 x power cord, 1 x omega bracket, 4 x screw, 4 x washer, 1 x remote control, 1 x battery

#### EUROLITE SB-10 Soft Bag

Black soft bag with divider, 330 x 330 x 355 mm

- Practical transport bag offers enough space for several lighting effects and accessories
- With divider
- With Outside pocket

### Logistic

EAN / GTIN: 4026397728507

Weight: 7,00 kg

Length: 0.00 m

Width: 0.00 m

Height: 0.00 m

- High-quality workmanship with nylon , black, water repellent
- Interior with foam padding
- 2 Rugged carrying handles

## Technical specifications:

---

Weight: 4,65 kg

---

### EUROLITE LED B-40 HCL Beam Effect MK2

|                       |  |
|-----------------------|--|
| Power supply:         | 100-240 V AC, 50/60 Hz   |
| Power consumption:    | 56 W   |
| IP classification:    | IP20   |
| Protection class:     | Protection class I   |
| Power connection:     | Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)   |
| Power output:         | IEC connector (F) mounting version   |
| Fuse:                 | T 1,6 A Fuse replaceable   |
| Lamp type:            | LED lamp   |
| LED:                  | 5 x 10 W 6in1 HCL RGBWA/UV   |
| Flash rate:           | 0 - 20 Hz  |
| DMX channels:         | 3; 12; 23  |
| DMX input:            | 1 x 3-pin XLR (M) mounting version   |
| DMX output:           | 1 x 3-pin XLR (F) mounting version   |
| Control:              | IR remote control; stand-alone; Sound to light via Microphone; DMX; QuickDMX via USB (optional); W-DMX by wireless solution via USB (optional); CRMX by LumenRadio via USB (optional); Master/slave function |
| Preprogrammed in:     | Light J; Light Captain; EASY SHOW 2; EASY SHOW 3   |
| Housing color:        | Black  |
| Attachment system:    | Omega bracket  |
| Display type:         | Monochrome 4 digit 7-segment LED display   |
| Dimensions:           | Length: 32,00 cm<br>Width: 32,00 cm<br>Height: 39,00 cm  |
| Weight:               | 4,22 kg  |
| Noise classification: | Class 2 (slight noise)   |
| Remote control        |  |
| Battery:              | 1 x Button cell 3.0 V CR2025 lithium manganese built-in  |
| Legal specifications  |  |
| Special product:      | Not designed for household room illumination   |
| Intended use:         | Show effect lighting   |

**EUROLITE SB-10 Soft Bag**

|                  |   |
|------------------|---|
| Maximum load:    | 25 kg   |
| Carrying handle: | 2 pc/pcs                                      |
| Material:        | Nylon   |
| Color:           | Black, water repellent                        |
| Dimensions:      | Width: 33 cm<br>Depth: 37 cm<br>Height: 33 cm |
| Weight:          | 440 g   |