

# OMNITRONIC Set PORTY-8A Drahtlos-PA-System + Bodypack Transmitter in oto Lawalier Mic

GTIN: 4026397739480



List price: 474.81 €

incl. 19% VAT.

#### Features:

#### **OMNITRONIC PORTY-8A Wireless PA System**

Mobile 8" PA system with battery operation, Bluetooth, DSP and wireless microphone

- Powerful sound in an ultra-compact package (114 dB max. SPL)
- Works great as primary PA system, stage monitor and practice amp
- 4-channel power mixer
- Stereo Bluetooth link for wireless stereo operation with 2 systems linked together
- UHF receiver unit and matching wireless microphone
- UHF 863 865 MHz License-free and approved in Europe
- Digital signal processor 96kHz, 24 bit
- DSP presets: FLAT; DJ; LIVE
- Cordless, flexible and versatile
- Integrated automatic charging of the battery and status indicator
- Battery operation up to 6,5h 50%; battery operation up to 3,5h 100%
- Black metal grille
- Bluetooth: operating range up to 20m
- Rugged carrying handle
- Lightweight plastic housing
- With tablet holder
- Dual flange
- Control via Bluetooth
- Application possibility: Standing; monitoring; on stand
- For application areas such as: Mobile use; mobile djs / entertainer; small rental; product presentations and lectures

#### Package contents

- 1 x compact cabinet speaker, 1 x microphone, 1 x power cord, 1 x user manual, 1 x declaration of conformity, 2 x battery, 1 x battery pack

## Logistic

EAN / GTIN: 4026397739480

Weight: 11,00 kg Length: 0.00 m Width: 0.00 m Heigth: 0.00 m

## OMNITRONIC PORTY-8A Bodypack + Lavalier Microphone 863.1 MHz

- Operating range up to 60m
- UHF 863 865 MHz License-free and approved in Europe

#### Package contents

- 1 x transmitter, 1 x microphone, 2 x battery, 1 x user manual, 1 x declaration of conformity

## **OMNITRONIC PORTY-8A Transport Bag**

- , black

## Package contents

- 1 x bag, 1 x strap

# **Technical specifications:**

Weight: 10,30 kg

## **OMNITRONIC PORTY-8A Wireless PA System**

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	Max. 220 W
Protection class:	Protection class I
Power connection:	Mains input via IEC connector (M) mounting version (provided)
	Battery/battery pack
Cable length:	1,5 m detachable
Device fuse:	5 x 20 mm, T 3,15 A fuse replaceable
Battery pack type:	1 x lithium ion 22,2 V, 4400 mAh, 97,68 Wh
Battery pack:	Battery operation up to 6,5h 50% Battery operation up to 3,5h 100% Recharging time 4h
Power:	120W RMS
Number of channels:	4
Frequency range:	45 - 18000 Hz
Max. SPL:	114 dB
DSP:	Digital signal processor 96kHz, 24 bit
DSP presets:	FLAT; DJ; LIVE
Control:	Bluetooth
Bluetooth:	Version: 5 with stereo link (TWS)
Bluetooth device name:	OMNITRONIC PORTY-8A
Range:	Bluetooth: range up to 20m
Frequency band:	UHF 863 - 865 MHz
Housing color:	Black
Attachment system:	Dual flange: Ø 35mm
Circuitry:	Class D

Control elements:	Power switch, Input sensitivity switch, Master control, level control per channel, echo effect control; connect
Connections:	Input: mic/line via 3 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version)
	Input: line via RCA (F) mounting version
	Input: line via 3.5 mm jack (stereo) mounting version
	Output: line via 3-pin XLR (M) mounting version
Channels:	Input chanel: 3 x mono with Mic-Line-Hi.Z. switch via Combination socket (XLR/jack), channel control via rotary dial, 2-band tone control EQ
Input channels:	1 x stereo via RCA or jack plug or Bluetooth, channel control via rotary dial
Speaker:	Woofer 8" with ferrit magnet
	8 x compression tweeter highs 1,35" with ferrit magnet
Type of speaker:	Wireless PA system
Carrying handle:	1 pc/pcs
Material:	Plastic
Dimensions:	Width: 29 cm
	Depth: 26,3 cm
	Height: 39,3 cm
Weight:	8,65 kg

# OMNITRONIC PORTY-8A Bodypack + Lavalier Microphone 863.1 MHz

	•
Cable length:	0,9 m detachable
Range:	Range up to 60m
Frequency band:	UHF 863 - 865 MHz
Carrier frequency:	863,1 MHz
RF power output:	10 mW
Color:	Black
Weight:	0,13 kg

# **OMNITRONIC PORTY-8A Transport Bag**

Color:	Black
Weight:	0,65 kg